

Aurora 6015 IP CC RGBWA USER MANUAL

Menu Parameters

| Address | | |
|-----------|--------------|-------|
| Test mode | Red | 0-255 |
| | Green | 0-255 |
| | Blue | 0-255 |
| | White | 0-255 |
| | Yellow | 0-255 |
| Sysi Info | Dmx Address | |
| | Running Mode | |
| | OnTime | |
| | RunTime | |
| | Temperature | 000 |
| | SoftVer | XF02 |

DMX Channel Chart

5 Channel Mode

| CH | Function | Description |
|----|--------------------|-----------------------------------|
| 1 | Dimmer | Dimmer, from dark to bright |
| 2 | Strobe | Strobe from slow to fast |
| 3 | Function Selection | No function |
| | | Color change |
| | | Color fade |
| | | Color pulse |
| 4 | Function Speed | Speed from slow to fast |
| 5 | Red Dimming | Red dimming, from dark to bright. |

9 Channel Mode

| CH | Function | Description |
|----|--------------------|------------------------------------|
| 1 | Dimmer | Dimmer, from dark to bright |
| 2 | Strobe | Strobe from slow to fast |
| 3 | Function Selection | No function |
| | | Color change |
| | | Color fade |
| | | Color pulse |
| 4 | Function Speed | Speed from slow to fast |
| 5 | Red Dimming | Red dimming, from dark to bright. |
| 6 | Green Dimming | Green dimming, from dark to bright |
| 7 | Blue Dimming | Blue dimming, from dark to bright |
| 8 | White Dimming | White Dimming, from dark to bright |
| 9 | Amber Dimming | Amber dimming, from dark to bright |