

## Table of Contents

Add a Device

### Scope:

Users in the system may own one or more SIP devices. These devices can be configured to ring together or separately according to the User's Answering Rules. In order to link a SIP device to a User's extension, you must add a [SIP Phone](#) to that User's profile.


### Requirements:

- Office Manager Access to Manager Portal
- Make and model of [SIP phone](#) (Optional)
- MAC address of [SIP phone](#) (Optional)


**NOTE:** There is a maximum of 5 devices per user

# Add a Device

1. Using any browser log into the manager portal
2. Click on **Users**



3. On the line with the user's name click on the **Edit** icon at the right and then click on Phones



4. Click **Add Phone**
5. If you are adding an additional device, you will need to enter a suffix. Simply select any letter in the alphabet that is not already in use.

Note that the following suffixes are reserved for system use: m, t, tm

**Add a Phone**



Phone Suffix

Note: This cannot be changed. Enter a unique suffix representing this device. i.e. "m" for mobile

6. For softphones & manually registered devices, just click **Add**, leaving all fields blank  
For provisioned devices:

- **Model:** Select the Make & Model of your device
- **MAC Address:** Enter the MAC Address of your device  
NOTE: This can typically be found on a sticker on the back of the phone.
- **Line Number:** 1

### Add a Phone ✕

Phone Suffix

Note: This cannot be changed. Enter a unique suffix representing this device. i.e. "m" for mobile

Record Calls

911 Caller ID  Leave blank to use default

Model

MAC Address

Line Number

The line number on which this phone will reside.

7. To view the registration information for a softphone or manually registered phone, edit the newly created device and note the **Domain/Proxy**, **Outbound Proxy**, **Username**, and **Password**

### Edit Phone ✕

Phone

Note: Phone Name cannot be changed

Record Calls

911 Caller ID  Leave blank to use default

Model

Settings

Domain/Proxy:

Outbound Proxy: sbc.ucaasnetwork.com:5060

Username: 3900a

Password:

Cancel

Save

calling device

sip phone