

SMART DMM**Smart Multimeter DMM 5400**

9999 Counts, mV/V/mA/A - AC(True RMS) / DC, Ω , Capacitance, Hz, $^{\circ}\text{C}$, NCV



LED Lighting

Input jack indicator

Never worry about inserting the wrong test lead
Smart Multimeter DMM 5400





Smart Multimeter DMM 5400



Smart Multimeter DMM 5400



Specifications	Range	Accuracy
DC Voltage	99.99mV/999.9mV; 9.999V/99.9V/1000V	±(0.5%+3)
AC Voltage	99.99mV/999.9mV; 9.999V/99.9V/750V	±(0.8%+3)
DC Current	9.999mA/99.99mA/600mA	±(0.8%+3)
	9.999A	±(1.2%+3)
AC Current	9.999mA/99.99mA/600mA	±(1.0%+3)
	9.999A	±(1.5%+3)
Resistance	99.99Ω/999.9Ω/9.999kΩ	±(0.8%+3)
	99.99kΩ/999.9kΩ	
	9.999MΩ/99.99MΩ	
Capacitance	0~99.99mF	±(4.0%+3)
	9.999mF/99.99mF	±(5.0%+5)
Frequency	99.99Hz/999.9Hz/9.999kHz/99.99kHz	±(1.0%+3)
	999.9kHz/9.999MHz	
Duty	1%~99%	±(1.0%+2)
Temperature	-40℃~1000℃	±(1.0%+3)
Counts		10000 Counts
Auto/Manual Range		Manual
Display		VA color Display Screen
Bargraph		√
Smart Function(AC/DC voltage,resistance and Continuity)		√
Live Test (Sound and Light Alarm)		√
NCV (Sound and Light Alarm)		√
Diode Test (Sound Alarm)		√
Continuity (Sound and Light Alarm)		√
MAX/MIN/AVG		√
Relative Measurement		√
Data Hold		√
True RMS		√
Fuse Burning Prompt Function		√
Input Jack LED Indication		√
Low Battery Indication		√
Auto Power Off		√
Double Color Backlight		√
Input Jack LED Indicate		√
Flashlight		√
Power:	3X1.5V AAA batteries	
Weight:	Approx.255g	
Size:	165mm*85mm*25mm	
Safety Rating: EN61010-1,-2-030 EN61010-2-033, EN61326-1 CAT III 1000V,CATIV 600V		



1. Non Contact Voltage Sensor
2. Power Key
3. Warning Indicator
4. Flash Light Key
5. Input Jack Indicator
6. Display
7. Function Key
8. Auto Power OFF Key
9. Flash Light Lamp
10. Input Jack (Other Then Current)
- 11.COM Jack
- 12.mA(<600mA) Jack
- 13.10A Jack