

7.5" LED Disk Light

Specifications



Model#	FDK-DLYY-F1-12-7.5-15-XXK-ZZ-D
Rated input voltage	AC120V 60Hz
Enter the maximum current Rated	0.15A
power	15W
Dimmable	TRIAC
CCT	3000K,4000K,5000K 1100lm 80/90
Rated flux	110°
Ra	≥3000h
The beam Angle	aluminum alloy, plastic PC
Rated life	Φ191*24.5mm
Material	~240G
Size	
Weight	
Using the environment temperature	-20℃-45℃
Using the environment	Indoor/Outdoor Damp Location
Storage temperature	-30℃-80℃
Store humidity	10-90%
Certification	ETL/cETL、FCC、Energy Star-V2.0
Warranty	5 year/ 30,000 hr




Order Information

Item Number	Description	Power	Voltage Input	Dimmable	CCT	Lumen Output	Certificates
FDK-DLYY-F1-12-7.5-15-XXK-ZZ-D	LED Disk Light	15W	120Vac	TRIAC	3000K,4000K 5000K	1100lm	ETL/cETL , Energy Star

*YY indicates the presence of JM or RM
JM meaning Junction Box Mount
RM meaning Recessed Mount

Product Size



7.5" LED Disk Light

Installation A: J-Box Mounting

1. Twist to detach the lamp shade (Part B) from the mounting plate (Part A) and set aside. (Figure 1)

2. CONNECTING THE WIRES

- Install the two screws (AA) into the junction box. (Figure 2)
NOTE: Leave 1/4" of screw exposed to accommodate mounting plate.
- Connect the house ground wire to the yellow/green ground wire on the mounting plate (Part A) using the wire nut (BB).
- Connect the house black wire to the mounting plate (Part A) black wire using the wire nut (BB).

3. ATTACHING THE MOUNTING PLATE

- Connect the house white wire to the mounting plate (Part A) white wire using the wire nut (BB).
NOTE: For proper connection, place the wire nuts (BB) over wires and twist clockwise until tight. (Figure 3)
OPTIONAL: Wrap connected wire nuts with electrical tape.

3. ATTACHING THE MOUNTING PLATE

- Attach the mounting plate to the junction box by aligning the holes on the mounting plate (Part A) with the screws on the junction box.
- Turn mounting plate clockwise to lock in place and tighten screws to ensure the fixture is secure and will not move. (Figure 4)

4. ATTACHING THE LAMP SHADE

Reattach lamp shade to mounting plate and twist to lock in place. (Figure 5)


7.5" LED Disk Light

Installation B: Recessed Mounting


CAUTION: Before beginning installation turn off the circuit breaker and light switch.

•Suitable for installation in the Recessed Installation of 5 inches, 6 inches.


1. Remove mounting bracket and plate from inside existing recessed housing (if installed).




2. Twist adaptor into socket.



3. Insert male connector into female one.




4. Squeeze friction blades together and install into recessed housing. Carefully route wires into fixture and push module up flush to ceiling surface.




7.5" LED Disk Light

Packaging


32pcs/CTN G.W.:14 kg Dimension: 21.7"L x 16.9"W x 17"H (550mm x 428mm x 435mm)




Container Loading QTY



Size	Carton QTY	Product QTY	Volume	G.W.
40'hq	648 ctn	20736 pcs	70.73 m ³	9072 kg



Size	Carton QTY	Product QTY	Volume	G.W.
40'gp	540 ctn	17280 pcs	58.94 m ³	7560 kg



Size	Carton QTY	Product QTY	Volume	G.W.
20'gp	260 ctn	8320pcs	28.38m ³	3640 kg