

TECHNICAL SPECIFICATIONS

STANDBY POWER

Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source,.Overload is not allowed.

PRIME POWER

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%.The generator can be overloaded 10% for 1 hour per 12 hrs.

CONTINUOUS POWER

Continuous power rating is used in applications where supplying power is at a constant 100% load for an unlimited number of hours each year. Continuous power rated units are most widely used in applications where the power grid is unreachable.



ENGINE

- BAUDOUIN heavy duty diesel engine
- 4-cycle, water cooled, turbo-charged
- Direct injection
- 24 Volt starter motor and charge alternator with battery, rack and cables
- Replaceable air, fuel and oil filter
- Industrial type radiator
- Flexible fuel piping
- Oil sump drain valve and extension pipe
- Industrial type exhaust silencer.
- Maintenance free battery
- Jacket Water Heater

ALTERNATOR

- Brushless, single bearing,4-pole alternator coupled with flexible disc coupling
- H type insulation class
- IP 21-23 protection
- Self exciting
- Electronic AVR

CONTROL PANEL

- DSE 7 Series mains sensing or remote start control module
- Emergency stop push button
- Output circuit breaker
- Static battery charger
- Ready for remote monitoring

CANOPY

- Modular type sound-proof canopy
- Built from galvanized steel and epoxy, polyester powder painted
- Lockable doors on both sides of canopy designed for easy access to essential replacement parts
- Emergency stop push button
- Control Panel viewing window
- Bunded base fuel tank (Optional)
- Forklift Pockets (Optional)



EA Power Systems reserves the right to make changes in model, technical specifications, color, equipment & accessories without prior notice

EA Power Systems Ltd.

207 Dominion Rd. LE36QA Leicester United Kingdom

www.eapowers.com +44(0)1163180570

Registered in England & Wales No:11023250



MOTEURS
Baudouin

MODEL		EAP1250	EAP1400	
OUTPUT	Standby	kVA	1250	1400
		kW	1000	1120
	Prime	kVA	1136	1273
		kW	909	1018
Engine		BAUDOUIIN	BAUDOUIIN	
Model		12M33G1250/5e2	12M33G1400/5e2	
Configuration		12 -V	12 -V	
No. of Cylinders		12	12	
Speed	rpm	1500	1500	
Displacement	l	39,2	39,2	
Bore x Stroke	mm	150 x 185	150 x 185	
Compression Ratio		15:1	15:1	
Aspiration		Turbocharged		
Governor Type		Electronic		
Cooling		Water		
Coolant Capacity	l	232,94	232,94	
Lubrication Oil Capacity	l	146	146	
Fuel Consumption l/h	100%Load	236,1	259,1	
	75% Load	174,9	191	
	50%Load	119,4	129,5	
ALTERNATOR	Phase		3	3
	Pole		4	4
	No. of Leads		12	12
	Excitation System		AVR	AVR
	Insulation Class		H	H
	IP Protection		IP23	IP23
	Power Factor		0,8	0,8
	Frequency	Hz	50	50
	Voltage	V	400	400
SIZE	Canopy Set Dimensions (LxWxH) & Weight	mm	5450 x 2400 x 3450	5450 x 2400 x 3450
		kg	8760	9080
	Open Set Dimensions (LxWxH) & Weight	mm	5000 x 2250 x 3450	5000 x 2250 x 3450
		kg	6450	6450
	Fuel Tank Capacity	l	2500	2500

EA Power Systems reserves the right to make changes in model, technical specifications, color, equipment & accessories without prior notice

EA Power Systems Ltd.

207 Dominion Rd. LE36QA Leicester United Kingdom

www.eapowers.com +44(0)1163180570

Registered in England & Wales No:11023250

CONTROL MODULE

Standard Specifications

- State of the art, microprocessor controlled
- 4line, 64 x 132 pixel display LCD display
- Automatic mains failure sensing
- Front panel manual programming
- User friendly setup and button layout
- Remote start
- Event logging, showing date and time
- Stop/Reset, Manual, Auto, Test, Start, buttons, toggle display button

Displays

- Engine Speed (rpm)
- Oil pressure
- Coolant temperature
- Running Hours
- Battery voltage monitoring
- Generator Voltage (LL, LN)
- Generator Current (L1-L2-L3)
- Generator Frequency (Hz)
- Generator Load & Power Monitoring (kW, kVA, kVAr, pf)
- Mains Voltage (LL, LN)
- Mains Frequency
- Generator Set Ready
- Mains Ready



Alarms

- High coolant temperature.
- Low oil pressure.
- Charge failure.
- Battery Low/High voltage.
- Fail to start/Fail to stop.
- Over Current
- High/Low Generator voltage.
- Generator Over/Under frequency.
- Generator Over/Under Speed.

Shut Downs

- Fail to start.
- Emergency stop.
- Low oil pressure.
- High coolant temperature.
- Generator Over/Under frequency.
- Generator Over/Under Speed.
- High/Low Generator voltage

EA Power Systems reserves the right to make changes in model, technical specifications, color, equipment & accessories without prior notice

EA Power Systems Ltd.

207 Dominion Rd. LE36QA Leicester United Kingdom

www.eapowers.com +44(0)1163180570

Registered in England & Wales No:11023250