

## TECHNICAL SPECIFICATIONS

### STANDBY POWER

Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source,.Overload is not allowed.

### PRIME POWER

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%.The generator can be overloaded 10% for 1 hour per 12 hrs.

### CONTINUOUS POWER

Continuous power rating is used in applications where supplying power is at a constant 100% load for an unlimited number of hours each year. Continuous power rated units are most widely used in applications where the power grid is unreachable.



### ENGINE

- PERKINS heavy duty diesel engine
- 4-cycle, water cooled, naturally aspirated
- Direct injection
- 24 Volt starter motor and charge alternator with battery, rack and cables
- Replaceable air, fuel and oil filter
- Industrial type radiator
- Flexible fuel piping
- Oil sump drain valve and extension pipe
- Residential type exhaust silencer.
- Maintenance free battery
- Jacket Water Heater

### ALTERNATOR

- Brushless, single bearing,4-pole alternator coupled with flexible disc coupling
- H type insulation class
- IP 21-23 protection
- Self exciting
- Electronic AVR

### CONTROL PANEL

- DSE 7 Series mains sensing or remote start control module
- Emergency stop push button
- Output circuit breaker
- Static battery charger
- Ready for remote monitoring

### CANOPY

- Modular type sound-proof canopy
- Built from galvanized steel and epoxy, polyester powder painted
- Lockable doors on both sides of canopy designed for easy access to essential replacement parts
- Emergency stop push button
- Control Panel viewing window
- Bunded base fuel tank (Optional)
- Forklift Pockets



EA Power Systems reserves the right to make changes in model, technical specifications, color, equipment & accessories without prior notice

EA Power Systems Ltd.

207 Dominion Rd. LE36QA Leicester United Kingdom

www.eapowers.com +44(0)1163180570

Registered in England & Wales No:11023250

MODEL		EAP1125	EAP1250	EAP1375	
OUTPUT	Standby	kVA	1125	1250	1375
		kW	900	1000	1100
	Prime	kVA	1022	1136	1250
		kW	818	909	1000
Engine		PERKINS	PERKINS	PERKINS	
Model		4008 - TAG2A	4008 - 30TAG3	4012 - 46TWG2A	
Configuration		INLINE	INLINE	12 - 60° V	
No. of Cylinders		8	8	12	
Speed	rpm	1500	1500	1500	
Displacement	l	30,561	30,561	45,842	
Bore x Stroke	mm	160 x 190	160 x 190	160 x 190	
Compression Ratio		13,6:1	13,6:1	13:1	
Aspiration		Turbocharged			
Governor Type		Electronic			
Cooling		Water			
Coolant Capacity	l	149	140	210	
Lubrication Oil Capacity	l	153	153	177	
Fuel Consumption l/h	100%Load	215	244	259	
	75% Load	162	188	199	
	50%Load	111	120	139	
ALTERNATOR	Phase		3	3	3
	Pole		4	4	4
	No. of Leads		12	12	12
	Excitation System		AVR	AVR	AVR
	Insulation Class		H	H	H
	IP Protection		IP23	IP23	IP23
	Power Factor		0,8	0,8	0,8
	Frequency	Hz	50	50	50
	Voltage	V	400	400	400
SIZE	Canopy Set Dimensions (LxWxH) & Weight	mm	5550 x 2200 x 2856	5550 x 2200 x 2856	TBA
		kg	9635	10025	TBA
	Open Set Dimensions (LxWxH) & Weight	mm	5300 x 2200 x 2640	5300 x 2200 x 2640	5350 x 2200 x 2750
		kg	8450	8480	9080
Fuel Tank Capacity	l	1950	2500	2500	

EA Power Systems reserves the right to make changes in model, technical specifications, color, equipment & accessories without prior notice

EA Power Systems Ltd.

207 Dominion Rd. LE36QA Leicester United Kingdom

www.eapowers.com +44(0)1163180570

Registered in England & Wales No:11023250

## CONTROL MODULE

### Standard Specifications

- State of the art, microprocessor controlled
- 4line, 64 x 132 pixel display LCD display
- Automatic mains failure sensing
- Front panel manual programming
- User friendly setup and button layout
- Remote start
- Event logging, showing date and time
- Stop/Reset, Manual, Auto, Test, Start, buttons, toggle display button

### Displays

- Engine Speed (rpm)
- Oil pressure
- Coolant temperature
- Running Hours
- Battery voltage monitoring
- Generator Voltage (LL, LN)
- Generator Current (L1-L2-L3)
- Generator Frequency (Hz)
- Generator Load & Power Monitoring (kW, kVA, kVAr, pf)
- Mains Voltage (LL, LN)
- Mains Frequency
- Generator Set Ready
- Mains Ready



### Alarms

- High coolant temperature.
- Low oil pressure.
- Charge failure.
- Battery Low/High voltage.
- Fail to start
- Fail to stop.
- High/Low Generator voltage.
- Generator Over/Under frequency.
- Generator Over/Under Speed.

### Shut Downs

- Fail to start.
- Emergency stop.
- Low oil pressure.
- High coolant temperature.
- Generator Over/Under frequency.
- Generator Over/Under Speed.
- High/Low Generator voltage

EA Power Systems reserves the right to make changes in model, technical specifications, color, equipment & accessories without prior notice

EA Power Systems Ltd.

207 Dominion Rd. LE36QA Leicester United Kingdom

www.eapowers.com +44(0)1163180570

Registered in England & Wales No:11023250