



SOLAR PRO 200Zb TW/CW

USER MANUAL

200W LED 25-50°zoom profile light



Operate instruction

• Package and accessories •

1. 200W LED zoom profile light25-50° 1 unit
2. 3 pin signal connector 1 pair
3. Power plug 1 pair

• Functions •

- ◆ Input voltage 100-240V 50-60HZ
- ◆ Power consumption 220W
- ◆ Manual zoom
- ◆ Zooming scale : 25-50°
- ◆ DMX dim or manual button dim
- ◆ 16 bit above no flicker linear dimming
- ◆ Inner size: 76×28.5×28.5cm
- ◆ G.W.: 14kg N.W.: 12kg













• Keys instruction •

 → Confirm
  → Function
  → Decrease
  → Increase

- ◆ Press Function key display different functions cyclically .
- ◆ Press decrease key and increase key to adjust each function's value .
- ◆ Press confirm key to confirm the function and value .

Special remind: when the multi units power cable mutual input / output connected ,each group can connect10 units, power cable must use 3 ×2.5²grounding .

• Screen display and its function •

No.	Screen	Function instruction
1	DMX-ADR 001 V	Already connect with DMX wire. press "  " and "  " keys can adjust address.
2	DMX-ADR 001 X	not connect with DMX wire. Can set master/slave connected, press "  " key or "  " key can adjust address you want.
3	ADJ-CW 255	Enter manual button dim mode press "  " key and "  "key to dim
4	DMX SING OFF/ON	Prior for DMX, press "  " or "  " choose the function DMX SING ON/OFF, and ten press "  " to save/confirm the function
5	DMX KEEP OFF/ON	for DMX keep/off, press "  " or "  " choose the function you want, and ten press "  " to save/confirm the function

• **DMX channels functions** •

Only 1 DMX channel 0-255 dim

• **Master/slave connect introduce** •

Set all units address same as "001", off DMX signal, can set any unit as master, set functions on the master unit by the Function key all units are synchronal