

18 WATT POWER AMPLIFIER, Type 18A1-L6PARTS LISTFor Drawing #602712

<u>Item</u>	<u>Part No.</u>	<u>Description</u>
C1	86135	.02 Mfd. Condenser, 400 v.
C2	85083	1000 Mmfd. $\pm 15\%$ Mica Condenser
C3	86155	.1 Mfd. 600 v. Condenser
C4	86155	.1 Mfd. 600 v. Condenser
C5	87564	20 Mfd. 25 v. Electrolytic
C6	86156	.005 Mfd. 1000 v. Condenser
C7	87566	30 Mfd. 450 v. Electrolytic
C8A)		(20 Mfd. 350 v. Electrolytic
C8B)	87565	(20 Mfd. 350 v. Electrolytic
C8C)		(20 Mfd. 25 v. Electrolytic
C9	87571	25 Mfd. 50 v. Electrolytic
C10	86163	1000 Mmfd. 200 v. Condenser
F1	12304	1-1/2 Amp. 3AG Fuse
L1	300051	Bass Choke
L2	300021	Filter Choke
M1	602721	Line Cord & Plug
P1	302108	Connector (Chassis)
P2	602718	2-Prong Connector
R1	82453	.27 Meg. $\pm 10\%$ 1/2 w. Resistor
R2	82418	330 Ohm $\pm 10\%$ 1/2 w. Resistor
R3	82442	33000 Ohm $\pm 10\%$ 1/2 w. Resistor
R4	82753	4700 Ohm $\pm 10\%$ 1 w. Resistor
R5	82813	10000 Ohm $\pm 10\%$ 2 w. Resistor
R6	82424	1000 Ohm $\pm 10\%$ 1/2 w. Resistor
R7	82464	2.2 Meg. $\pm 10\%$ 1/2 w. Resistor
R8	82109	330 Ohm $\pm 20\%$ 1/2 w. Resistor
R9	82109	330 Ohm $\pm 20\%$ 1/2 w. Resistor
R10	82675	82000 Ohm $\pm 5\%$ 1/2 w. Resistor
R11	82675	82000 Ohm $\pm 5\%$ 1/2 w. Resistor
R12	82674	10000 Ohm $\pm 5\%$ 1/2 w. Resistor
R13	82674	10000 Ohm $\pm 5\%$ 1/2 w. Resistor
R14	81084	125 Ohm $\pm 10\%$ 5 w. W.W. Resistor
R15	82746	1000 Ohm $\pm 10\%$ 1 w. Resistor
R16	82432	4700 Ohm $\pm 10\%$ 1/2 w. Resistor
S3	602326	11-Prong Socket
S4	84244	9-Prong Socket
SW1	602705	Remote Speaker Switch
T1	300041	Input Transformer
T2	602707	Output Transformer
T3	302012	Power Transformer
TS1	602715	Terminal Strip