



EpsilonR- Transmitting The Talent
 10 Cumberland Place, Southampton
 SO15 2BH, United Kingdom
 Engineering@EpsilonR.com
 www.EpsilonR.com

Waveguide Filters-Transmit/Receive/Harmonic

Model No	Category	Name	BANDPASS FREQUENCY (GHz)	B-P INSERTION LOSS (dB)	VSWR (Max)	WAVEGUIDE SIZE (EIA/RCSC)	STOPBAND FREQ. (GHz)	REJECTION (dB Max)	SEC. HARMONIC REJECT. (dB Max)
0913100	Filters	Waveguide Filters-Receive	5.850-6.425	0.1	1.1	WR159/WG13	3.700-4.200	80	
0914100	Filters	Waveguide Filters-Receive	5.850-6.425	0.1	1.1	WR137/WG14	3.700-4.200	80	
0914200	Filters	Waveguide Filters-Receive	6.725-7.025	0.1	1.1	WR137/WG14	4.500-4.800	80	
0915100	Filters	Waveguide Filters-Receive	7.900-8.400	0.3	1.1	WR112/WG15	7.250-7.750	55	
0917100	Filters	Waveguide Filters-Receive	14.000-14.500	0.2	1.1	WR75/WG17	10.000-12.200	80	
0917200	Filters	Waveguide Filters-Receive	14.000-14.500	0.3	1.1	WR75/WG17	10.000-12.750	60	
1011100	Filters	Waveguide Filters-Transmit	3.625-4.200	0.1	1.1	WR229/WG11A	5.850-6.425	60	
1011200	Filters	Waveguide Filters-Transmit	3.700-4.200	0.1	1.2	WR229/WG11A	5.925-6.425	80	
1011300	Filters	Waveguide Filters-Transmit	4.400-5.000	0.15	1.1	WR229/WG11A	6.720-7800	60	
1011400	Filters	Waveguide Filters-Transmit	4.500-4.800	0.1	1.1	WR229/WG11A	6.720-7800	60	
1015100	Filters	Waveguide Filters-Transmit	7.250-7.750	0.45	1.2	WR112/WG15	7.900-8.400	60	
1017100	Filters	Waveguide Filters-Transmit	10.000-12.750	0.2	1.12	WR75/WG17	14.000-14.500	60	
1017200	Filters	Waveguide Filters-Transmit	11.525-12.375	0.2	1.12	WR75/WG17	14.000-14.500	70	
1017300	Filters	Waveguide Filters-Transmit	12.250-12.750	0.2	1.12	WR75/WG17	14.000-14.500	70	
1111100	Filters	Waveguide Filters-Harmonic	3.540-4.200	0.2	1.12	WR229/WG11A			65
1111200	Filters	Waveguide Filters-Harmonic	3.700-4.200	0.2	1.12	WR229/WG11A			65
1112100	Filters	Waveguide Filters-Harmonic	4.400-5.000	0.2	1.15	WR187/WG12			50
1114100	Filters	Waveguide Filters-Harmonic	5.900-6.450	0.2	1.12	WR137/WG14			65
1114200	Filters	Waveguide Filters-Harmonic	6.400-7.200	0.2	1.12	WR137/WG14			60
1115100	Filters	Waveguide Filters-Harmonic	7.000-8.200	0.2	1.12	WR112/WG15			40
1115200	Filters	Waveguide Filters-Harmonic	7.600-8.400	0.2	1.12	WR112/WG15			65

Model No	Category	Name	BANDPASS FREQUENCY (GHz)	B-P INSERTION LOSS (dB)	VSWR (Max)	WAVEGUIDE SIZE (EIA/RCSC)	STOPBAND FREQ. (GHz)	REJECTION (dB Max)	SEC. HARMONIC REJECT. (dB Max)
1117100	Filters	Waveguide Filters-Harmonic	12.000-13250	0.2	1.20	WR75/WG17			40
1117200	Filters	Waveguide Filters-Harmonic	14.000-14.500	0.2	1.15	WR75/WG17			65
1118100	Filters	Waveguide Filters-Harmonic	14.000-14.500	0.2	1.15	WR62/WG18			65
1118200	Filters	Waveguide Filters-Harmonic	14.000-15.400	0.2	1.15	WR62/WG18			40
1119100	Filters	Waveguide Filters-Harmonic	17.630-19.700	0.5	1.15	WR51/WG19			40
1120100	Filters	Waveguide Filters-Harmonic	18.000-24.000	0.5	1.44	WR42/WG20			30
1120200	Filters	Waveguide Filters-Harmonic	19.000-22.000	0.3	1.15	WR42/WG20			50
1120300	Filters	Waveguide Filters-Harmonic	21.000-24.000	0.3	1.50	WR42/WG20			25
1120400	Filters	Waveguide Filters-Harmonic	21.200-23.600	0.5	1.15	WR42/WG20			40
1121100	Filters	Waveguide Filters-Harmonic	25.000-28.000	0.5	1.15	WR34/WG21			50
1122100	Filters	Waveguide Filters-Harmonic	29.000-30.000	0.3	1.40	WR28/WG22			30
1122200	Filters	Waveguide Filters-Harmonic	37.000-39.500	0.5	1.20	WR28/WG22			40