

Max Effect FP10000



Features

- Stable performance in 4ohms at low temperature
- Pure copper ring toroidal transformer
- Customised design heat aluminium (heatsink)
- Customised fans
- Original Toshiba transistors that provides the best sound quality



THE QR CODE
GENERATOR

Specification

8Ω Stereo	4x1000W
4Ω Stereo	4x1500W
8Ω Bridge	3000W
Output Circuitry	Class H
Frequency Response	10Hz-30kHz±1db
Input Sensitivity	0.775V/1.0V/1.4V
Balanced	20KΩ
Unbalanced	10KΩ
Crosstalk	≥65dB 8Ω 1KHz
S/N Ratio	≥101dB
Damping Factor	≥800
Total Harmonic Distortion	<0.5%@8Ω 1/10 Pro
Slew Ratio	25V/u S