



# CONNECTED Processing Services, Inc.

3419 Westminster, Suite 369G Dallas, TX 75209 1-833-226-6328

## GenMega Quick Reference Guide

### Customer Setup

- 1. Change Processor**
  - a. Communication: **SSL Pass Through**
  - b. Message Format: **Standard 3**
  - c. SSL Data Format: **8 Bits**
  - d. Reversal on Host Error: **Enable**
    - i. SSL Version: **TLS 1.2**
    - ii. SSL Certification: **Disabled**
  - e. Standard 3 Option
    - i. Comm. Header: **Enable**
    - ii. Status Monitor: **Enable**
    - iii. Use 12 Sequence Number: **Disabled**
    - iv. Use TCP/IP CRC: **Disabled**
- 1. Surcharge Mode**
  - a. Surcharge Mode: **Enable**
  - b. Surcharge Owner: **User Preference**
- 2. Optional Function ▶ EMV**
  - a. EMV: **Enable**

### System Setup

- 1. Change Password**
  - a. Change ALL passwords to unique values
- 2. Device Setup ▶ ATM TCPIP Setup**
  - a. TCPIP Mode: **DHCP**
  - b. **Press APPLY** to save changes!
- 3. Serial Number**
  - a. Serial Number: Input serial number listed on the sticker inside of the top cabinet
- 4. Set Clock**
  - a. Set current date and time (24hr time format)

### Transaction Setup

- 1. Dispense Limit: \$200**
- 2. Low Currency Check:**
- 3. Denomination:** Be sure to open Vault Door and remove cassette when changing denomination type

### Host Setup ▶ ATM Host

- 1. Terminal Number: Unique TID**
- 2. Routing ID: CPSATM**
- 3. Host IP Address**
  - a. Host IP Address #1: **atm.cpsatm.com**
  - b. Host Port #1: **30001**
  - c. Host IP Address #2: **atm.cpsatm.com**
  - d. Host Port #2: **30001**
  - e. **Press Download Key**
    - Ensure the key exchange was successful
- 4. Health Check: Enable**
- 5. Remote Monitor**
  - a. RMS: **Enable**
  - b. RMS Status Send: **Enable**
  - c. RMS Ports: Default
  - d. RMS Host: 216.169.5.84

### Key Management

- 1. Change Passwords:** Both passwords need to be different from each other, and cannot be left at default (000000)
  - a. Key Mode: **TDES**
  - b. Edit Key
  - c. Master Key Part A
  - d. Choose whatever index you prefer  
\*\*Must use the same index for each key part\*\*
  - e. Type all 32 digits from Master Key Part One
  - f. Press Master Key Part B and type all 32 digits from Master Key Part Two  
\*\*\*Be sure to use the same Input Index as before\*\*\*

### Settlement

- 1. Set Cassette**
  - a. Set Cassette #1 (or applicable cassette number)
  - b. Set Cash 1, 2, etc.: Enter number of bills loaded in the cassette
  - c. Press Enter