



# CONNECTED Processing Services, Inc.

3419 Westminister, Suite 369G Dallas, TX 75209 1-833-226-6328

## Hyosung Standard 1 Quick Reference Guide

### Customer Setup

- 1. Select Processor**
  - a. Communication: **TCP/IP**
  - b. Message Format: **Standard 1**
  - c. EOT/ENQ Options:
    - i. TCPIP Type: **Visa-Framed**
    - ii. Press **CANCEL**
    - iii. EOT/ENQ Option: **No ENQ Required / EOT Required**
    - iv. Press **CANCEL**
  - d. TCPIP Type: **Standard**
  - e. SSL/TLS: **Enable**
  - f. SSL/TLS Version: **Up to TLS V1.2**
  - g. SSL/TLS Cert: **Disable**
- 2. Standard 1 Option**
  - a. Terminal Status: **Enable**
  - b. Reversal At Host Error: **Enable**
  - c. Reason For Reversal: **Enable**
  - d. Press : **Extended Functions**
    - i. Dynamic Call: **Enable**
    - ii. 1<sup>st</sup> Call: **Disable**
    - iii. Currency Conversion: **Enable**
      - Option: **General**
      - Local Surcharge: **Disable**
      - DCC Type: **Mastercard Only**
- 3. Surcharge Mode**
  - a. Mode: **Enable**
  - b. Owner: **User Preference**
- 4. Optional Function1 > EMV**
  - a. EMV: **Enable**
  - b. Kernel Version: **V6.0**
  - c. Language Selection: **Enable**
  - d. Press **OTHER OPTIONS**
    - i. Use Common AID: **Enable**
    - ii. US Territory: **US**
    - iii. Unknown IC Card: **Fallback**
    - iv. Fallback: **Enable**

### System Setup

- 1. Change Password**
  - a. Change all passwords to unique values
- 2. Terminal IP**
  - a. DHCP: **Enable**
- 3. Serial Number**
  - a. Input serial number listed on the sticker inside of the top cabinet
- 4. Date & Time**
  - a. Set clock to current date and time (24hr time format)

### Transaction Setup

- 1. Dispense Limit:  $\geq$  \$200**
- 2. Low Currency Check: User Preference**
- 3. Denomination:** Be sure to open Vault Door and remove cassette when changing denomination type

### Host Setup

- 1. Terminal Number:** Enter unique TID
- 2. Host Address**
  - a. URL: **Enable**
  - b. Host IP Address #1: **atm.cpsatm.com**
  - c. Host Port #1: **30001**
  - d. Host IP Address #2: **atm.cpsatm.com**
  - e. Host Port #2: **30001**
- 3. Routing ID: CPSATM**
- 4. Health Check: Enable**
- 5. Remote Monitor**
  - a. RMS: **Enable**
  - b. ATM Listening Port: **5555**
  - c. RMS Status Send: **Enable**
  - d. Server Listening Port: **9999**
  - e. RMS Host Address: **216.169.5.84**

### Key Management

- 1. Enter Master Keys**
  - a. Enter Password 1 and 2: 000000 (Default)
  - b. Change Password 1 & 2
  - c. Press **CANCEL** twice and wait 30 seconds
  - d. Log back into Key Management menu using new **passwords**
  - e. Key Mode: **TDES (3)**
  - f. **Edit Key > Master Key Triple > MasterK3 > Yes**
  - g. Press **Entry** and type all 32 digits from Key Part 1
  - h. Press **Import**
  - i. Press **Entry** and type all 32 digits from Key Part 2
  - j. Verify check digits match

### Settlement

- 1. Add Cash**
  - a. Select applicable cassette(s)
  - b. Type in proper bill count and press **OK > APPLY**