

Norstar CICS Wiring (Control Unit)

Amphenol 1 (Left)

<u>Pair</u>	<u>Color</u>	<u>Designation</u>
1	White/Blue	Line 001
2	White/Orange	Line 002
3	White/Green	None
4	White/Brown	None
5	White/Slate	Line 003
6	Red/Blue	Line 004
7	Red/Orange	None
8	Red/Green	None
9	Red/Brown	Line 025
10	Red/Slate	Line 026
11	Black/Blue	None
12	Black/Orange	None
13	Black/Green	Line 027
14	Black/Brown	Line 028
15	Black/Slate	None
16	Yellow/Blue	None
17	Yellow/Orange	Emergency Transfer
18	Yellow/Green	None
19	Yellow/Brown	None
20	Yellow/Slate	Internal ATA
21	Violet/Blue	None
22	Violet/Orange	None
23	Violet/Green	Music-On-Hold
24	Violet/Brown	Ext. Paging Relay (Make = V/B, Common = B/V)
25	Violet/Slate	Ext. Paging Audio

Norstar CICS Wiring (Control Unit)

Amphenol 2 (Right)

<u>Pair</u>	<u>Color</u>	<u>Designation (Defaults)</u>
1	White/Blue	Station 21/221/2221
2	White/Orange	Station 22/222/2222
3	White/Green	Station 23/223/2223
4	White/Brown	Station 24/224/2224
5	White/Slate	Station 25/225/2225
6	Red/Blue	Station 26/226/2226
7	Red/Orange	Station 27/227/2227
8	Red/Green	Station 28/228/2228
9	Red/Brown	Station 29/229/2229
10	Red/Slate	Station 30/230/2230
11	Black/Blue	Station 31/231/2231
12	Black/Orange	Station 32/232/2232
13	Black/Green	Station 33/233/2233
14	Black/Brown	Station 34/234/2234
15	Black/Slate	Station 35/235/2235
16	Yellow/Blue	Station 36/236/2236
17	Yellow/Orange	Station 37/237/2237
18	Yellow/Green	Station 38/238/2238
19	Yellow/Brown	Station 39/239/2239
20	Yellow/Slate	Station 40/240/2240
21	Violet/Blue	Station 41/241/2241
22	Violet/Orange	Station 42/242/2242
23	Violet/Green	Station 43/243/2243
24	Violet/Brown	Station 44/244/2244
25	Violet/Slate	Aux Ringer (Make = V/S, Common = S/V)

J & J Communications
770-795-5462 or 888-552-6665
www.jandjcommunications.com