

# Winlink Express Tactical Addresses & Auxiliary Call Signs Setup & Use

Georgia ARES Digital Messaging Training



# Benefits of Tactical Address

- Provide functional identification (e.g., NSH-DULUTH vs KK4FGL)
- Alternative\* when a club call is not available for use
- Facilitates shared usage without risk of changing a call sign associated account.
- When Winlink Express checks for incoming messages it receives both messages addressed to the user's primary call sign and any enabled tactical addresses.
- CMS server will not accept creating a tactical address already registered in system.
  - Once you have obtained a tactical address, it is yours until deleted or expires.



# Tactical Address Account @ Winlink.org

- Tactical address created with password have login account @ winlink.org.
- Log into tactical address account, provide:
  - Contact information
  - Recovery email address
- Having email address on file provides method to recover forgotten password.

## NSH-DULUTH

[View](#) [Edit](#) [Track](#)

**Full licensed name:**  
**Street address 1:**  
**Street address 2:**  
**City:**  
**State:**  
**Country:**  
**Postal code:**  
**E-mail address:**  
**Grid square:**  
**Phones:**  
**Web site:**  
**Comments:**  
**Call prefix:**  
**Call suffix:**  
**PW Recovery e-mail:**  
  
**Alternate (temporary forwarding) e-mail:**  
**Maximum message size:**



# What is a Tactical Address

Winlink has specific requirements for tactical addresses:

- Tactical Addresses are all caps 3 to 12 total characters long.
- Tactical Format:
  - May be alpha only characters (minimum 3, A-Z)
  - Optionally a “-” (dash) followed by alphanumeric characters (A-Z, 0-9)
  - No numbers to the left of the “-” (dash)
  - No spaces or special characters
- Examples
  - Valid: NSH-DULUTH, GEMA, LOOKOUT-1, GWINNETT-EOC
  - Invalid: THISISTOOLONG, RESTSTOP1 (missing “-” before numeric)

# Tactical Address: Add Entry

1. Open Winlink Express Settings
2. In Auxiliary Call Signs and Tactical Addresses select Add Entry



The main dialog box is titled "Winlink Express Properties". It has several sections:

- Call Signs:** Includes fields for "My Callsign:" (N7GRB), "My Password:" (masked with dots), "Callsign suffix (optional):", and "Password recovery e-mail:" (redacted). There are "Remove Callsign" and "Request password be sent to recovery e-mail" buttons.
- Auxiliary Callsigns and Tactical Addresses:** A list box contains "GNR-HEALTH". To its right are "Add Entry", "Remove Entry", and "Edit Entry" buttons. A blue arrow points from the "Add Entry" button in this section to the inset dialog box.
- My Grid Square:** Field contains "EM74XA".
- Winlink Express registration key:** Field is redacted.
- Service Codes:** Field contains "PUBLIC".


The inset dialog box is titled "Auxiliary Callsign or Tactical Address". It contains:

- A text field for "Callsign/Tactical Address:".
- A "Password:" field (Case sensitive) with a "Show password" checkbox.
- An "Enabled:" checkbox which is checked, with the note "(Enabled entries download incoming messages)".
- "Save" and "Cancel" buttons.

# Tactical Address: Complete Entry

1. Enter Tactical Address, Password, Enabled then select Save
2. Tactical Addresses window will indicate with a check mark the enabled aux call signs and tactical addresses

1



Auxiliary Callsign or Tactical Address

Callsign/Tactical Address: NSH-DULUTH|


Password: ●●●●●●●●  
(Case sensitive)  Show password

Enabled:

(Enabled entries download incoming messages)

Save Cancel

2




Auxiliary Callsigns and Tactical Addresses

GAAUXC  
 GNR-HEALTH  
 NSH-DULUTH

Add Entry  
Remove Entry  
Edit Entry





## Tactical Address: Enable / Disable

1. Select Tactical Address to enable or disable
2. Select **Edit Entry**
3. Check **Enabled** or uncheck as needed then **Save**



Auxiliary Callsigns and Tactical Addresses

- GAAUXC
- GNR-HEALTH
- NSH-DULUTH

Add Entry  
Remove Entry  
Edit Entry



Auxiliary Callsign or Tactical Address

Callsign/Tactical Address: NSH-DULUTH|

Password: ●●●●●●●●  
(Case sensitive)  Show password

Enabled:

(Enabled entries download incoming messages)

Save Cancel







## Tactical Address: Sending Message

1. N7GRB selects in **From** drop-down list NSH-DULUTH tactical address.
2. W4HBS receives message from sender NSH-DULUTH.

(Note actual call sign of the sender, N7GRB, is listed as **Source** thus FCC is happy.)



Enter a new message

Close Select Template ICS 213 ICS214A Check-In ICS309 Attachments Post

From: N7GRB Send as: Winlink Message  Request message rec

To: N7GRB  
NSH-DULUTH

Cc:

Subject: 213-Georgia ARES Hospital Net-August Hospital Net

Attach: RMS\_Express\_Form\_ICs213\_Initial\_Viewer.xml;

GENERAL MESSAGE (ICS 213)




EIG1Z0C397SH - 213-Georgia ARES Hospital Net-August Hospital Net - 2021-08-01

Close Print View Attachments Reply Reply All Acknowledge Forward

Message ID: EIG1Z0C397SH  
Date: 2021/07/18 01:00:00  
From: NSH-DULUTH  
To: W4HBS  
Source: N7GRB  
Subject: 213-Georgia ARES Hospital Net-August Hospital Net


GENERAL MESSAGE (ICS 213)





# Tactical Address Usage Considerations

1. Only enable the tactical address (or auxiliary call sign) when you are the designated on-shift station operator to which the tactical address (or auxiliary call sign) is associated.
  - Two or more users with same tactical address enabled results in races to grab messages from the CMS server.
  - Disable the tactical address when not in use or you otherwise hand-off responsibility to another operator (shift change)
2. Tactical address password
  - Tactical address has a Winlink.org login, password needed for security
  - Changing the password in your Winlink Express may affect ability of others to use the shared tactical address



# Tactical Address Considerations

## 3. Tactical Address vs primary Call Sign account

- A tactical address is associated with the primary Winlink account under which the tactical address is enabled.

### Example:

- NSH-DULUTH is a tactical address created by and usage associated with KK4FGL (a club call sign)
- N7GRB uses his own primary Winlink account with tactical address HSH-DULUTH enabled
- N7GRB will receive messages addressed to N7GRB and NSH-DULUTH but not to KK4FGL

## 4. Peer-to-Peer sessions do not support tactical addresses.



# Auxiliary Call Signs

- An auxiliary call sign is a normal (FCC) Winlink call sign account.
- Used as a secondary address for sending / receiving messages.
- Auxiliary call sign entries are entered, enabled and disabled similar to the tactical addresses

Auxiliary Callsigns and Tactical Addresses

<input type="checkbox"/> GAAUXC	<input type="button" value="Add Entry"/>
<input type="checkbox"/> GNR-HEALTH	
<input checked="" type="checkbox"/> KK4FGL	
<input checked="" type="checkbox"/> NSH-DULUTH	



# Auxiliary Call Sign Example Usage

Usage example (monthly hospital net):

- Due to hospital pandemic access restrictions N7GRB, representing Northside Duluth hospital, is operating remotely at home QTH.
- Northside Duluth has club call KK4FGL and tactical address NSH-DULUTH
- In N7GRB's primary Winlink setup, he has the club call KK4FGL set as an auxiliary call sign and NSH-DULUTH as tactical address
- When N7GRB runs a session, message traffic for his primary call, the auxiliary call and tactical address are sent and received.



# Auxiliary Call Sign Example Usage

Edit a draft message entered by N7GRB

Close Select Template Attachments Post to Outbox Spell Check Save in Drafts

From: N7GRB Send as: Winlink Message  Request message receipt Set Defaults

To: N7GRB  
KK4FGI  
KK4FGK

Cc: KK4FGL  
NSH-DULUTH

Subject: ARES Hospital Net-August Hospital Net - 2021-08-01 16:00

Attach: RMS\_Express\_Form\_ICs213\_Initial\_Viewer.xml;


- N7GRB creates hospital net check in, ICS-213 message, and submits
- In message **To:** field enters **W4HBS**
- In message **From:** drop down list selects auxiliary call sign **KK4FGL**  
(note same process for using tactical address NSH-DULUTH)



# Auxiliary Call Sign Example Usage

Date/Time	Message ID	Size	Source	Sender	Recipient	Subject
2021/07/27 17...	MRWWKAQS...	1319	N7GRB	KK4FGL	W4HBS	213-Georgia ARES H

- W4HBS receives KK4FGL hospital net check in message
  - **Sender** is listed **KK4FGL**
  - **Source** is **N7GRB** (FCC is happy)



*Questions?*