



Primate Power[®] Source

Primate Power[®] Sources are rugged, compact, and efficient.

- SiC power devices
- 19" rackmount enclosures
- Fully bi-directional
- Rack systems available
- Built-in displays & keypads
- Built-in interface connectors

4 kW 1 phase AC - 3 phase 4 wire AC / DC with built-in fuses and isolation

- Input 1 phase 200 VAC to 240 VAC
- Output 3 phase AC or DC 12 A
- 2U enclosure: 3.5" x 19" x 18"

12 kW 3 phase AC - 3 phase 4 wire AC / DC with built-in fuses and isolation

- Input 3 phase 200 VAC to 240 VAC
- Output 3 phase AC or DC 35 A
- 6U cabinet: 12.5" x 21" x 24.5"

18 kW 3 phase AC - 3 phase 4 wire AC / DC with built-in fuses and isolation

- Input 3 phase 200 VAC to 240 VAC
- Output 3 phase AC or DC 50 A
- 8U cabinet: 16" x 21" x 24.5"

30 kW 3 phase AC - 3 phase 4 wire AC / DC with built-in fuses and isolation

- Input 3 phase 200 VAC to 240 VAC
- Output 3 phase AC or DC 85 A
- 13U cabinet: 24.8" x 21" x 24.5"

75 kW 3 phase AC - 3 phase 4 wire AC / DC with built-in fuses

- Input 3 phase 200 VAC to 240 VAC
- Output 3 phase AC or DC 210 A
- 20U cabinet: 40.2" x 21" x 24.5"

75 kW 3 phase AC - 3 phase 4 wire AC / DC with built-in fuses

- Input 3 phase 380 VAC to 480 VAC
- Output 3 phase AC or DC 90 A
- 20U cabinet: 40.2" x 21" x 24.5"

150 kW 3 phase AC - 3 phase 3 wire AC / DC with built-in fuses

- Input 3 phase 380 VAC to 480 VAC
- Output 3 phase AC or DC 180 A
- 24U cabinet: 47.2" x 21.4" x 24.5"

300 kW 3 phase AC - 3 phase 3 wire AC / DC with built-in fuses

- Input 3 phase 380 VAC to 480 VAC
- Output 3 phase AC or DC 360 A
- 32U cabinet: 62.2" x 21.4" x 24.5"

www.PrimatePowerSource.com

preliminary data sheet