

VST3 · AU · Version 1.0 · Mzane Electric

Occams Phazor

Dual phaser · Parallel or series · Stereo width

Two independent phasers with depth, speed, feedback, and series/parallel linking for rich stereo sweeps.

www.mzanelectric.com · info@mzanelectric.com



Occams Phazor interface

1. Welcome

Occams Phazor is a dual-phaser effect. Units A and B can run side by side on left and right (parallel) or cascade A into B (series). Depth, speed, feedback, and link mode shape evolving stereo phasing.

This guide covers installation, the interface, every control, and practical tips. No developer tools or project setup are required.

Key features

- Two phaser paths (A and B) with independent depth and speed
- Shared feedback control
- Parallel (L/R) or series (A→B) linking
- Visual phase and status indicators
- Activation and trial through your Mzane Electric account

What you will need

- A DAW that loads VST3 (and AU on macOS).
- Occams Phazor installed from your official Mzane Electric download.
- Audio on the track or bus where you insert the plugin.

2. Installation

After purchase (or a trial download), get the package from your Mzane Electric account or product page on www.mzanelectric.com. Always install from the official download.

macOS

- Unzip the download. You will typically find both a **.vst3** and a **.component** (AU).
- VST3: copy into /Library/Audio/Plug-Ins/VST3/ (or your user Library VST3 folder) as **OccamsPhazor.vst3**.
- AU: copy into /Library/Audio/Plug-Ins/Components/ (or your user Library Components folder) as **OccamsPhazor.component**.
- Logic Pro and GarageBand use AU; many other DAWs use VST3.

Windows

- Unzip the Windows package.
- Copy **OccamsPhazor.vst3** into C:\Program Files\Common Files\VST3\.

Restart your DAW or rescan plugins. If macOS asks for permission the first time, allow it and try again.

Tip: If the UI does not update after an install, remove the plugin from the track and insert it again.

3. Activation & Trial

Occams Phazor is activated through your Mzane Electric account. Without an active trial or full license, audio processing is disabled.

- Open the plugin in your DAW.
- If it is not yet activated, the activation window will appear. You can also click **License** at any time.
- Sign in or create your Mzane Electric account.
- Start a free trial, or unlock the full version after you have purchased.
- If you already bought Occams Phazor with the same account, full access should unlock automatically.

Purchase on www.mzanelectric.com. After buying, download from your customer library, install, then activate in the plugin with the same account. For help, email info@mzanelectric.com.

4. Interface overview

A hardware-style panel with knobs, toggles, phase indicators, and status lights, plus License.



Figure — Occams Phazor interface.

Regions at a glance

Area	What you see
A Phase / A Speed	Depth and LFO rate for Phaser A.
B Phase / B Speed	Depth and LFO rate for Phaser B.
Feedback	Resonance intensity for the phaser paths.
Connect A→B	Off = parallel stereo · On = series cascade.
Bypass	Dry comparison.
Indicators	Phase motion, bypass, and link status.

Drag knobs **vertically** to adjust values. Your DAW saves and recalls settings with the project.

5. Quick start

1. Insert Occams Phazor on a track or bus.
2. Start in parallel (Connect off) with modest Phase depth and slow Speeds.
3. Raise Feedback carefully for more intensity.
4. Enable Connect A→B for a thicker, cascaded sweep.
5. Try different A and B Speeds for evolving, contrasting motion. Use Bypass to A/B.

6. Controls reference

Knobs respond to vertical drag. Ranges below are approximate; your DAW may show host-normalized values depending on the control.

Control	Range	What it does
A Phase	0 ... 1	Depth of Phaser A modulation.
A Speed	0.1 ... 10 Hz	How fast Phaser A's LFO sweeps.
B Phase	0 ... 1	Depth of Phaser B modulation.
B Speed	0.1 ... 10 Hz	How fast Phaser B's LFO sweeps.
Feedback	0 ... 1	Feeds phaser output back into the input. Start low.
Connect A to B	Off / On	Off: A left / B right (parallel). On: A into B (series).
Bypass	Off / On	Disables processing for dry comparison.

7. Usage tips

- Parallel mode: wide stereo with different A/B settings left and right.
- Series mode: stacks both phasers for a deeper sweep.
- Slow A Speed + faster B Speed for evolving motion.
- Automate Phase, Speed, or Connect for movement through a song.

Troubleshooting

Issue	What to try
No sound	Confirm activation (License). Check Bypass, mute, Level/Mix, and that audio is playing.
Plugin not found	Rescan plugins. Use AU in Logic/GarageBand; VST3 elsewhere. Verify install folders.
Activation problems	Sign in with the purchase account. Re-open License. Email info@mzanelectric.com .
macOS blocks plugin	Re-download the official release and install again. Allow permission if prompted.

Support & product info

Product	Occams Phazor
Format	VST3 + AU (macOS) · VST3 (Windows)
Manufacturer	Mzane Electric
Version	1.0
Website	www.mzanelectric.com
Support	info@mzanelectric.com

Thank you for using Occams Phazor. For product support, contact Mzane Electric.