NOW AVAILABLE

Fastlane Audio R-ATT

Precision Stepped Midrange Attenuator

Fixed-resistor L-pad • 1 dB steps



3–18 dB	8 Ω / 16 Ω	30 W	50 W
Attenuation • 1 dB steps	Selectable driver impedance	Estimated continuous input	Estimated music power

Switch settings

Select 8 Ω or 16 Ω to match the driver. Turn on only the A–D switches shown.

ATTENUATION	SWITCHES ON
3 dB	None
4 dB	A
5 dB	B
6 dB	A + B
7 dB	C
8 dB	A + C
9 dB	B + C
10 dB	A + B + C
11 dB	D
12 dB	A + D
13 dB	B + D
14 dB	A + B + D
15 dB	C + D
16 dB	A + C + D
17 dB	B + C + D
18 dB	A + B + C + D

Change settings with the amplifier off.

fastlaneaudio.com