



# **BLINDER 200 TW/CW**

USER MANUAL  
2X100W COB TW/CW LED



# 200W Single color Led Blinder Audience Light

## DMX Channels

CH	Index	Description
CH1	0-255	Dimmer
CH2	0-255	Strobe
CH3	0-255	Sound active
CH4	0-255	Speed
CH5	0-255	White 1
CH6	0-255	White 2

## LED DISPLAY

MENU:

UP: +

DOWN:-

ENTER:



UP or DOWN

ENTER

MENU

A001	→	D512	DMX512
A-CH	→	Channel optional	2/4/6CH
CC00	→	CC99	Gradual change
CP00	→	CP99	Pulse change
DE99	→	DE99	Jump change
BEBE	→	BEBE	Sound active
Y255	→	Y255	Warm white dimmer
R255	→	R255	White dimmer
On/off	→	Switch	Turn on/turn off

## Function and characteristics

Control signal: 4 standard DMX512 channel controls

Control mode: DMX intelligent signal automatic detection, built-in automatic program, voice control (special effects)

Dimming: 0-100% electronic dimming, each color can be dimmed individually or in combination

Strobe: 1-25 times / sec high-speed strobe, can be monochrome, mixed color temperature strobe

Display panel: LED display panel