

**GENERATOR SPECIFICATION**

Voltage	230/115
Phase	1
Frequency	50Hz
Prime Power (PRP)	2.5 kVA / 2.0 kW
Alternator	NSM K80B
Alternator Type	Brushless - Smooth Waveform
Fuel tank capacity	3.1 Litres
Autonomy 75% load	3.1 Hours
LWA	96
dBA @ 7M	71

**ENGINE SPECIFICATION**

Engine	Honda GP160
Emissions certified	N/A
Cylinders	Single
Distribution	O.H.V.
Aspiration	Normally aspirated
Cooling	Air
Displacement	163 cm <sup>3</sup>
Rpm	3000
Starting system	Recoil
Fuel	Unleaded 86 octane or higher



**DIMENSIONS (mm)**

DIMENSIONS (mm)			WEIGHT (KG)
Length	Width	Height	34
610	420	415	



24 Months Non-Commercial Engine Warranty (Limited)  
3 Months Commercial Engine Warranty (Limited)

**CONTROL BOX (Plastic)**

- 1 x 16A 230V & 1 x 16A 115V BS4343 sockets.
- Reset circuit breaker overload protection.
- Voltage selector switch.

**STANDARD FEATURES**

- Oil alert/low oil shutdown.
- Full wrap-around frame.
- Brushless smooth waveform alternator.

**OPTIONS**

- Single voltage.
- Trolley kit.

**POWER DEFINITION**

**Prime Power (PRP) :** Applicable for supplying power to varying electrical load for unlimited hours in accordance ISO 8528-1 under the agreed operating conditions with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.

\* UKCA approved - not for sale in the EU