













- Digital Video Recording & CCTV Systems
- Remote Surveillance Via Internet & Networks
- Camera Installation & Service
- Portable Surveillance
- Custom Manufactured Installations
- Wireless Communication
- Industrial & Mining
- Home & Commercial
- Integrated Alarms

Sales: Office 02 4942 1797 Email: enquiries@jetcctv.com.au Accounts: ac@jetcctv.com.au

2/7 Revelation Close Tighes Hill NSW 2297 Master Licence - 409176554

# www.jetcctv.com.au



# 1.1– Playback Video Footage on your recorder

 Right Click anywhere on the screen to bring up the menu and log on screen. Use the mouse to enter the RECORDER's admin password "admin1234" with the on-screen keyboard and click OK. (admin is the default username and admin1234 is the default password.) If you have changed your password, use that one.



2. Once logged in, right click to open the menu dropdown left click Main menu and select SEARCH





3. You will now see the RECORDER search screen. The arrow indicates the calendar in which you can select the month and day you wish to playback. Any date highlighted blue has video available to playback.



4. Once you have selected the day, you can choose which cameras you wish to playback by clicking the D1, D2, D3 or D4 box etc.



5. Finally you can select the time, from the time bar at the bottom of the screen. You will notice that the hours are listed from 00:00 to 24:00. Simply clicking on the bar will display the video footage from that time. A green bar will indicate that there is video and the yellow bar indicated movement at that time.





## 1.2 – How to Backup Video Footage on your recorder

In order to backup Video Footage from your Recorder you will first require a USB Stick or USB Hard drive 9we strongly recommend having a FAT32 file system).

 Right Click anywhere on the screen to bring up the menu and log on screen. Use the mouse to enter the RECORDER's admin password "admin1234" with the on-screen keyboard. (admin is the default username and admin1234 is the default password.) If you have changed your password, use that one.



2. Once logged in, right click to open the menu dropdown left click Main menu and select BACKUP.

N'VA		
PLAYBACK Wew, search, and play recorded videos.	AI Manage and view artificial intelligence and face recognition information and settings.	ALARM View and search live alarm information. Configure alarm event actions.
OPERATION View System info, System update and Config import/export etc.	BACKUP Search and back up video files.	DISPLAY Configure resolution and display settings.
	• •	
MANAGEMENT CAMERA 😗 NETWORK	🗧 🚔 STORAGE 🛛 🎝 SYSTEM	1 🧕 ACCOUNT

3. You will now see the Recorder Backup Device where you can choose the device you wish to backup to.



#### Choose your device and Click

N'177	BACKUP	1					L G - ;;;
	Device Name	sdb1(USB USB)	1	Format	8.98 GB/14.42 GB(Free/	Total)	
	Path			Browse			
6	Record C	D1					
	Туре	All		Main Stream			
	Start Time	04 - 03 - 2020 00 : 00 : 00		End Time	04 - 03 - 2020 10 : 1	6:49	
	File Format	DAV			Search	Clear	
	0 Ch	annel Type Start Time		End Time	Size(KB)	Play	
Γ,							
MANA							
	0.00 KB(Space	e Needed)			Опекеу Васкир	Васкир	

## 4. The following screen will appear. Click

N'V#		LIVE
PLAYBACK Wew, search, and play recorded Videos. Find USB device. POPERATION View System info, System and Config import/expo Config Backup (Find USB device)	AI Manage and view artificial sdb1(USB USB) ty: 8.98 GB/14.42 GB(Free/Total) ckup Log Backup ackup System Upgrade	ALARM View and search live alarm information. Configure alarm event actions. DISPLAY Configure resolution and display settings.
MANAGEMENT CAMERA 6 RETWORK	🚔 STORAGE 🛛 🎄 SYSTEM 🛛 💄	ACCOUNT

## 5. Select date and time required for backup.

∧' <i>\\</i> #	BACKUP							1 (• • #1
	Device Name	sdb1(USB USB)		Format	8.98 GB/14.42 G	B(Free/T	otal)	
	Path			Browse				
6	Record C	D1						
	Туре	All		Main Strea	m			
	Start Time	04 - 03 - 2020 10 : 30 : 00	•	End Time	04 - 03 - 2020	10:40	:49	
	File Format	DAV			Sea	irch	Clear	
-	0 Ch	annel Type Start T.me		End Time	Size	(KB)	Play	
<b>É</b> ,		Se	lect St	art date / t	ime and End da	ate / tin	ne	
MANA								
	0.00 KB(Space	e Needed)			Onekey B	ackup	Backup	

6. Select Camera Channel for backup

N'1/7	BACKUP				L (→ 58
	Device Name Path	sdb1(USB USB)	Format Browse	8.98 GB/14.42 GB(Free/Total)	
Q	Record C Type	D1 D1 D2 D3 D4 All	Main Strea	Select Camera	
-	Start Time File Format	04 - 03 - 2020 00 : 00 : 00 DAV	End Time	04 - 03 - 2020 10 : 16 : 49 Search Clea	r
C,	0 Cha	annel Type Start Time	End Time	Size(KB) Play	
MANA	0.00 KB(Space	: Needed)		Onekey Backup Backu	ıp

7. Click SEARCH to display your selection.

Device Name		sdb1(USB	USB)		Format 8.98 GB/1	4.42 GB(Free/1	"otal)		
	Path		Browse						
6	Record C D1								
	Туре	All	All		Main Stream 🔹				
Start Time File Format		04 - 03 - 2020 10 : 30 : 00			End Time 04 - 03 -	04 - 03 - 2020 10 : 40 : 49			
		DAV	AV.			Sealth	Clear		
	11 √ Ch	annel Type	Start Time		End Time 🧹	Size(KB)	Play		
ſ,			04-03-2020 10:32:03		04-03-2020 10:32:07	3776			
			04-03-2020 10:32:07		04-03-2020 10:32:23	9152			
			04-03-2020 10:32:23		04-03-2020 10:3 .32				
	4 √D1		04-03-2020 10:32:32		04-03-2020 10 33:57	40960			
MANA	242.00 MB(Sp	ace Needec	i) Cl	ick spla	Search to On ay selection	ekey Backup	Backu	р	

8. Once you have selected the footage to be backed up, press BACKUP to begin the transfer process.

Device Name Path		sdb1(USB USB)			Format 8.98 GB/14.42 GB(Free/Tot				⊺otal)				
						Browse							
6	Record C	D1											
	Туре	All				Main Stream	ı						
Start Time		04 - 03 - 2	2020	10:30:00		End Time	me 04 - 03 -		3 - 2020 10 : 4				
		DAV						Sea	arch	Clear			
0	11 √ Ch	annel Typ	oe Star	t Time		End Time		Size	e(KB)	Play			
			04-0	3-2020 10:32:03		04-03-2020 1							
			04-0	3-2020 10:32:07		04-03-2020 1	0:32:23						
			04-0	3-2020 10:32:23		04-03-2020 1	0:32:32						
			04-0	3-2020 10:32:32		04-03-2020 1	0:33:57	409	60				
MANA	242.00 MB(Space Needed)					o	nekey B	lackup	Back	p			
					c	lick to start	Backu	р 🥢					