



## Affordable 2 to 10 station Systems

- ✓ Performance
- ✓ Durability
- ✓ Value
- ✓ Compatibility

**Performance:** An econoCom system consists of: 1) a table-top (ECADAPTER) AC adaptor with removable IEC power cord, and a cable with connector which connects the ECADAPTER to the PS4 interface box, and; 2) a PS4 system interface. These two devices, taken together, are the system's power supply. Also included are two, three or four of our standard *full-featured* BP1 belt packs, and a headset, with connector, for each belt pack. The systems are also available without head-sets. **The system does include a signal light feature.**

The econoCom power supply components are not intended to be used in systems which include more than two loudspeaker stations or stage manager stations, and do not provide multiple circuits. **One to six more BP1 belt packs (for a maximum total of ten) may be added to the system without creating hum or overheating the power supply components.** Older belt-packs, particularly those with incandescent (rather than LED) signal lamps should be added with caution as they draw much more current. The AC adaptor provides up to 1.0A of current at a nominal 24VDC. It is UL<sup>®</sup> CE and CSA<sup>®</sup> approved. It has universal input, operating at any voltage from 100 to 240VAC at either 50 or 60 HZ. The PS4 system interface provides precise voltage regulation, further smoothing of the DC current (AC hum elimination), automatic overload/short-circuit protection, the necessary termination network for the intercom circuit, an LED indicator which indicates that 24VDC is being delivered, and 3 paralleled XLR jacks for connection of headset stations or strings of stations in a party-line configuration. **The components of an econoCom system are connected together using standard 2-conductor shielded microphone cables fitted with 3 pin XLR connectors (male/female).** The PS4 has 3 Male XLR's which are in parallel and the BP1s have a male and a female XLR for connecting to the PS4 and for looping on-wards to the next BP1.

**Durability:** The ribbed, extruded aluminum case, polypropylene end bezels, internal support system for the PC boards, and best quality XLR connectors all contribute to the outstanding ability of the system components to withstand rough usage.

**Value:** The comparatively low price of an econoCom system is made possible by the minimized assembly costs resulting from simplicity of construction. Simple construction also affords the use of higher quality components, and increases the ease (thus lowering the cost) of servicing.

**Compatibility:** The econoCom AC adaptor and PS4 system interface are fully compatible with Clear-Com<sup>®</sup> and other popular (200 unbalanced) party-line headset intercom systems.

**Pro Intercom LLC**  
 PO Box 7035 Algonquin Illinois 60102-7035  
 Phone: +1 (815) 680-5205    Orders and Tech support: (888) 320-5928    Fax: +1 (815) 526-8689  
 support@prointercomllc.com    Skype: intercom4pros

Printed in U.S.A. Rev.3\_01.13