



### **EZ 701**

Max Load: 10A, 230V

Accepts 2 Loop Cables and 1 Load Cable

0.5mm<sup>2</sup> to 1.5mm<sup>2</sup> max

2 core 3 core or twin & earth

Features Lever Lid™ and Color-Coded Terminals

Clear Lid for Quick Inspection

Male and Female, Plug & Play IP50 Connector

3 Year Guarantee

Intended for single use only

No Enclosure Required



**SCAN WITH CAMERA FOR INSTALLATION VIDEO**

Written Technical Safety and Installation Instructions (Overleaf)

UK Design Registration 6323587, BS 5733:2010, Patent pending



## Installation Instructions: **EZ 701**

Installation by Electrician or Competent Person Required  
Wiring Must Follow IEE Wiring Regulations

### **Isolate electrical supply before commencing installation.**

1. Strip the outer sheath of the flex to 30mm.
2. Strip the inner insulation to 8mm as indicated in the connector.
3. Use a screwdriver at the rear to gently release the lid clamps.
4. Lift the lever lid.
5. Insert the stripped cable into the correct color-coded connector.
6. Push the cable firmly to the backstop.
7. Use the V grip cable clamp to trap the flex by pushing the outer sheath downwards.
8. Close the lid, pushing down on both rear corners to secure it.
9. Repeat for both loop cables and the load cable.
10. Click both male and female connectors together.
11. Reinstate the supply.
12. Test for correct operation.

