



BD5 SERIES BUSINESS DIGITAL RADIO

SIMPLE, ROBUST, CLEAR-VOICE



Hytera's BD5 series two-way radio is the compact device that provides a professional communication in easy-operation way. Today, communication tool is the key to improve the efficiency. When we ask for clear voice, it means a reliable talk with easy-to-hear and –understand. Long battery life always helps you to avoid something out of control. A rugged and robust device gets the worry out of mind. High-performance but simple operation will make everything easy to go.

Hytera understands customers' requirements and meets them all in one, also with lightweight, easy-operation, excellent performance, long-time working and reliability. So we redefine a business radio with Hytera digital technology, quickly responding to what you need.



BD50X

BD55X

EXCELLENT PERFORMANCE

With innovative design, BD5 series has a better performance than analog radios. An excellent receiving ability makes the communication range further extended. What's more, it is a DMR digital radio with good performance of anti-interference, providing purely stable communication.

RUGGED AND RELIABLE

BD50X/BD55X is designed and tested to meet Military Standards 810 C, D, E, F and G, including temperature shock, vibration, high & low temperature and humidity. IP54 dust- and water-proof design guarantees the reliability in different environments. And based on TDMA technology, the radio can work longer, up to 22 hours in digital mode.

CLEAR VOICE

With digital encoding and correction technology, human voice is transmitted much clearer without noise, even in a rather far distance. This is a new experience of better audio quality.



ANTENNA
Enhance signal receiving ability.

CHANNEL KNOB
Support 16 channels to be changed very easily.

LED INDICATOR
Show the radio receiving and transmitting status as green light and red light.

SPEAKER AND MICROPHONE
Provide clear receive and transmit audio.

LIMITLESS CHANNEL SELECTOR
Up to 256 channels can be selected via continuous rotation.

POWER ON/OFF, VOLUME UP/DOWN

AUDIO JACK
Support different kinds of earpiece and remote speaker.

DISPLAY
Support displaying channel alias, caller ID and alias, zone number, battery indicator, high/low power.

PUSH-TO-TALK BUTTON
Easy to find and touch.

PROGRAMMABLE BUTTON
It can be programmed as a useful function as you like.

BD50X

BD55X

PROFESSIONAL AND SIMPLE TO USE

A/D ANALOG & DIGITAL DUAL MODES
BD50X/BD55X can support both analog and digital modes on the same hardware. You can switch between two operation modes very easily and it helps you to communicate with analog radios.

ANALOG & DIGITAL AUTO DETECT
BD50X/BD55X can detect the signal type when receiving a call, then automatically switches between analog mode and digital mode to get the voice out of speaker. During the call hang time, user can easily reply the call by push-to-talk. This is a real migration technology from analog to digital.

EXTENDED TALK RANGE
Based on Hytera innovative technology, extremely extend your talk range.

LONG WORKING TIME
Based on TDMA technology, BD5 series in digital mode can work as long as 16 hours @1500mAh or 22 hours @2000mAh in 5-5-90 mode.

CLEAR VOICE
Excellent audio quality comes from the DMR digital technology, which makes the communication more reliable.

RELIABLE AND DURABLE
BD50X/BD55X is compliant with MIL-STD-810 C/D/E/F/G and IP54.

ANTI-INTERFERENCE
Adopted digital encoding and error correcting module, BD5 series can have a better ability to avoid signal interference on the same frequency.

DMR DMR SIGNALING
With DMR signaling, transmitting group call, private call and all call with PTT ID becomes quite easy.

REPEATER MODE OPERATION
Utilize a DMR Tier II repeater to extend your communication range.

VOICE ANNOUNCEMENT (only for BD50X)
Channel number announcement helps you to switch channels quickly and correctly, even in blindness operation.







DUAL CAPACITY DIRECT MODE
In direct mode, you can have two voice calls simultaneously from DMR two time slots. This feature can be used to increase the radio capacity at no extra costs or frequency license.

VOX
This feature allows you to activate the radio microphone via speaking volume, and free your hand from PTT.




















SCANNING
Allow BD5 series listening to communication activities on other channels.

ACCESSORIES

STANDARD ACCESSORIES

 <p>AN0435W09 Whip Antenna, 400-470MHz,^① 16cm</p>	 <p>BL1506 1500mAh Li-ion battery</p>	 <p>CH10L23 BD50X standard drop-in single unit charger</p>	 <p>BC08 Belt clip</p>	 <p>RO03 Nylon hand strap</p>	 <p>Power Adapter input: 100-240VAC, output: 12VDC/1A <i>US/UK/AU/EU/CHINA/JAPAN /KOREA</i></p>
--	---	--	--	---	---

OPTIONAL ACCESSORIES

 <p>EHM15 D-style earpiece with in-line PTT & MIC <i>VOX switch</i></p>	 <p>EHM18 C-style earpiece with in-line PTT & MIC <i>VOX switch</i></p>	 <p>ESM12 Ear-bud with PTT on MIC <i>VOX switch</i></p>	 <p>EAM12 Ear-bud with PTT on MIC <i>VOX switch</i></p>	 <p>EAM13 2-wire surveillance earpiece <i>VOX switch</i></p>
 <p>ACM-01 PTT&MIC-only with 3.5mm jack <i>Ip54</i></p>	 <p>ES-01 Receive-only ear-bud</p>	 <p>ES-02 Receive-only surveillance earpiece</p>	 <p>EH-01 Receive-only C style earpiece</p>	 <p>EH-02 Receive-only earhook speaker</p>
 <p>PC76 Data programming cable</p>	 <p>SM08M3 Remote speaker microphone <i>with 3.5mm audio jack</i></p>	 <p>SM26M1 Remote speaker microphone <i>Ip54 with 3.5mm audio jack</i></p>	 <p>LCBN13 Universal nylon chest Pack</p>	 <p>NCN011 Nylon carrying jacket</p>
 <p>BL2018 2000mAh Li-ion battery</p>	 <p>MCL19 BD50X multi-unit charger</p>	 <p>AN0435H13 Stubby antenna,400-470MHz,^① 9cm</p>	 <p>CHV09 Vehicle adapter (Input: 11-25V DC, Output: 12V DC & 1A)</p>	

① AN0435H13: 400-470MHz, 9cm AN0141H06: 136-147MHz, 17cm AN0167H06: 160-174MHz, 17cm AN0153H08 AN0153H08: 147-160MHz/1575MHz, 12cm
AN0435W09: 400-470MHz, 16cm AN0153H07: 147-160MHz, 17cm AN0160H14: 146-174MHz, 15cm AN0167H07 AN0167H07: 160-174MHz/1575MHz, 12cm

SPECIFICATION

General	
Frequency Range	UHF:400-470 MHz VHF:146-174 MHz
Channel Capacity	BD50X: 48, BD55X: 256
Zone Capacity	BD50X: 3, BD55X: 16
Channel Spacing	25/12.5KHz
Operating Voltage	7.2V
Display	BD50X without display BD55X with display (0.91")
Battery	1500mAh (Li-Ion) 2000mAh (Li-Ion)
Battery Life (5/5/90)	Analog/Digital: 12/16 hours (1500mAh) 16/22 hours (2000mAh)
Weight	BD50X: 240g, BD55X: 250g (With AN0435W09 and BL1506)
Dimensions	BD50X: 108×54×28mm BD55X: 110×59×30mm
Frequency Stability	±0.5ppm
Antenna Impedance	50Ω
Receiver	
Sensitivity (Digital)	0.22μV / BER 5%
Sensitivity (Analog)	0.22μV (Typical) (12dB SIN AD) 0.4μV (20dB SIN AD)
Adjacent Selectivity	TIA-603 60dB @ 12.5KHz/70dB @ 25KHz
Spurious Response Rejection	TIA-603 70dB @ 12.5/25KHz
Inter-modulation	TIA-603 65dB @ 12.5/25KHz
Hum & Noise	40dB @ 12.5KHz 45dB @ 25KHz
Rated Audio Power Output	0.5W
Rated Audio Distortion	≤3%
Audio Response	+1 ~ -3dB
Conducted Spurious Emission	<-57dBm

Transmitter	
RF Power Output	VHF High power: 5W VHF Low power: 1W UHF High power: 4W UHF Low power: 1W
FM Modulation	11K0F3E @ 12.5KHz 16K0F3E @ 25KHz
4FSK Digital Modulation	12.5KHz Data Only: 7K60FXD 12.5KHz Data & Voice: 7K60FXW
Conducted/Radiated Emission	-36dBm <1GHz, -30dBm >1GHz
Modulation Limiting	±2.5KHz @ 12.5KHz ±5.0KHz @ 25KHz
FM Hum & Noise	40dB @ 12.5KHz 45dB @ 25KHz
Adjacent Channel Power	60dB @ 12.5KHz, 70dB @25KHz
Audio Response	+1 ~ -3dB
Audio Distortion	≤3%
Digital Vocoder Type	AMBE++
Digital Protocol	ETSI-TS102 361-1,-2,-3

Environmental	
Operating Temperature	-30°C~ +60°C
Storage Temperature	-40°C~ +85°C
ESD	IEC 61000-4-2 (Level 4) ±8kV (Contact) ±15kV (Air)
Dustproof & Waterproof	IP54 Standard
Humidity	Per MIL-STD-810 C/D/E/F/G Standard
Shock & Vibration	Per MIL-STD-810 C/D/E/F/G Standard

BD50X/BD55X, X=0, 2, 5, 6 or 8, model number varies geographically. For details, please contact our regional sales representatives.

All specifications are subject to change without notice due to continuous development.



Hytera Communications Corporation Limited

Address: Hytera Tower, Hi-Tech Industrial Park North, Beihuan Rd.,
Nanshan District, Shenzhen, China

Tel: +86-755-2697 2999 Fax: +86-755-8613 7139 Post: 518057

Http: //www.hytera.com Stock Code: 002583.SZ



Hytera retains right to change the product design and specification. Should any printing mistake occur, Hytera doesn't bear relevant responsibility. Little difference between real product and product indicated by printing materials will occur by printing reason.

HYT, Hytera are registered trademarks of Hytera Communications Co., Ltd.
© 2013 Hytera Communications Co., Ltd. All Rights Reserved.