

## Voltage monitor KUV NU 142



### Technical information

#### Operating voltage

180 ... 240 V AC

#### Power consumption

approx. 1 VA

#### Time delay

< 1 s

#### Voltage dropout

180 V AC

#### Relay outputs

230 V / 5A / AC

#### Ambient temperature

-20 ... +55 °C

#### Housing dimensions

W / H / D 23 x 75 x 100 mm

| Description                                                                                                                                                                                                                                                                                                                              | Ordering information          |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------|
| <p>The KUV NU 142 mains monitor monitors the mains voltage for the 3 phases, L1, L2, L3 and the neutral conductor. In the event of a fault, the relay falls back after &lt; 1 second and the LED fault lamp lights up.</p> <p>The operating manual can be downloaded on our Homepage <a href="http://www.kuhse.de">www.kuhse.de</a>.</p> | <p>KUV NU142 : 2W142UU000</p> |