

MTP / MPO Patch Cables

Multi-fiber MTP / MPO Assemblies feature cables terminated with MTP / MPO connectors, suitable for both indoor and outdoor settings. They provide convenient plug-and-play functionality, eliminating the need for on-site termination and splicing, reducing deployment costs. Their high-density design minimizes network footprint, making them ideal for central office, head-end, and data center installations.

Features

- Standard | Elite & Ferules
- OS1 | OM1 - OM5
- G.657.A1 | G.657.A2 | G.657.B3 | G.651
- Corning and Prysmian Fiber
- Tested for insertion loss, return loss & end-face
- Flame-retardant OFNR & OFNP
- Available in indoor & indoor/outdoor jackets
- Available in armor & non-armor



Part Number Configurator

M P O - 1 1 - 2 2 - 3 3 - 4 - 5 5 - 6 6 6 6 - 7 7 7 7 - 8 - 9 9 9 9 - M / F

1 Jacket Type

- IR = Indoor Riser
- IP = Indoor Plenum
- OR = Indoor/Outdoor Riser
- OP = Indoor/Outdoor Plenum

2 Fiber Type

- S1 = Singlemode G.657.A1
- B1 = Singlemode G.657.A2
- B3 = Singlemode G.657.B3
- M1 = Multimode (50) OM1
- M2 = Multimode (62.5) OM2
- M3 = Multimode (50) OM3
- M4 = Multimode (50) OM4
- M5 = Multitmode (50) OM5

3 Fiber Count

- 12 = Microcore 12 Fiber Round
- 24 = Microcore 24 Fiber Round

4 Armor

- 0 = Non-armored
- A = Armored

5 Jacket Size & Color

- 3A = 3.00mm Aqua
- 3O = 3.00mm Orange
- 3R = 3.00mm Rose
- 3L = 3.00mm Lime
- 3S = 3.00mm Yellow
- 3B = 3.00mm Blue
- 3X = 3.00mm Black

6 MPO Connector A

- S12A = Standard 12 Fiber MPO Female Method A
- S12B = Standard 12 Fiber MPO Female Method B
- S12C = Standard 12Fiber MPO Female Method C
- E12A = Elite 12 Fiber MPO Female Method A
- E12B = Elite 12 Fiber MPO Female Method B
- E12C = Elite 12 Fiber MPO Female Method C
- S241 = Standard 24 Fiber MPO Female Option 1
- S242 = Standard 24 Fiber MPO Female Option 2
- E241 = Elite 24 Fiber MPO Female Option 1
- E242 = Elite 24 Fiber MPO Female Option 2

7 MPO Connector B

- LCU2 = 12/24 LCU 12inch 2mm breakout
- LCA2 = 12/24 LCA 12inch 2mm breakout
- SCU2 = 12/24 SCU 12inch 2mm breakout
- SCA2 = 12/24 SCA 12inch 2mm breakout
- S12A = Standard 12 Fiber MPO Female Method A
- S12B = Standard 12 Fiber MPO Female Method B
- S12C = Standard 12 Fiber MPO Female Method C
- E12A = Elite 12 Fiber MPO Female Method A
- E12B = Elite 12 Fiber MPO Female Method B
- E12C = Elite 12 Fiber MPO Female Method C
- S241 = Standard 24 Fiber MPO Female Option 1
- S242 = Standard 24 Fiber MPO Female Option 2
- E241 = Elite 24 Fiber MPO Female Option 1
- E242 = Elite 24 Fiber MPO Female Option 2
- XXXX = No Connector

8 Boot Type

- S = Short
- R = Regular

9 Cable Length

- XXXF = Feet
- XXXM = Meters