

LT1E Line-interactive UPS Series



The LT1E series, featured with smart microprocessor control design, AVR boost and Buck, Smart RS232/USB interface and cold start function, is a cost-effective solution to your mission-critical PC and valuable peripherals.

Features

- **AVR Boost and Buck**
Automatically corrects either under-voltage or over-voltage condition without unnecessary battery drain and extend the life of the battery.
- **Cold Start Function**
Aids users to turn on the UPS without connecting the Utility.
- **Smart RS232/USB Interface for Power Management**
Supports real-time power and UPS status monitoring. Automatic shutdown, schedule and many other advance power management functions. The RS232 & USB ports of 1.2KVA up can be enabled simultaneously.
- **Built-in Self-diagnostic Function**
May execute automatically upon power-on or software-control.
- **Auto-restart Function**
The UPS will be automatically re-started when Utility recovers.
- **Compatible with Generator Set**
LT1E series supports wide range input voltage to fit with various generator sets.
- **Models with LCD Display are Available Now**
With comprehensive graphic display, it provides easy read-out status of the UPS from the screen, such as input voltage, output voltage, load level, battery leve... ..etc..
- **Fastest Charging Capacity**
With built-in powerful charger, the UPS can be fully charged back to 90% in 6-8 hours.
- **Auto Charging at Off Mode**
The battery may be charged continuously even though it is at OFF mode.
- **Modem/LAN Internet Protection**
Protects the Modem/LAN against spike or surge coming through network or telephone wires.

LT1E Line-interactive UPS Series

LT1E 400 | LT1E 600 | LT1E 800 | LT1E 1000 | LT1E 1200
LT1E 1500 | LT1E 2000 | LT1E 2400 | LT1E 3000

LT1E Line-interactive UPS Series

	LT1E								
Model	LT1E 400	LT1E 600	LT1E 800	LT1E 1000	LT1E 1200	LT1E 1500	LT1E 2000	LT1E 2400	LT1E 3000
Capacity	400VA	600VA	800VA	1000VA	1200VA	1500VA	2000VA	2400VA	3000VA
INPUT									
Voltage	110/120 VAC or 220/230/240 VAC								
Voltage range	81-145 VAC / 162-290 VAC								
Frequency range	60/50 Hz (auto sensing)								
OUTPUT									
AC Voltage Regulation (Batt. Mode)	±10%								
Frequency Range(Batt. Mode)	60 Hz or 50 Hz ±1 Hz								
Transfer Time	Typical 2-6 ms, 10ms max.							Typical 10 ms, 13 ms max.	
Waveform (Batt. Mode)	Simulated Sine Wave								
BATTERY									
Battery Type & Number	12 V/4.5AH x 1	12 V/7AH x 1	12 V/9AH x 1	12V/7AH x 2	12 V/7AH x 2	12 V/9AH x 2	12 V/9AH x 2	12 V/7AH x 4	12 V/9AH x 4
Typical Recharge Time	6-8 hours recover to 90% capacity								
INDICATORS									
AC Mode	Green LED lighting								
Battery Mode	Amber LED flashing					Green LED flashing			
Fault	Red LED lighting								
PROTECTION									
Full Protection	Overload and overcharge protection								
ALARM									
Battery Mode	Sounding every 10 seconds								
Low Battery	Sounding every second								
Overload	Sounding every 0.5 second								
Battery Replacement Alarm	Sounding every 2 seconds								
Fault	Continuously sounding								
PHYSICAL									
Dimension (W x H x D) mm	101 x 142 x 298			149.3 x 162 x 338		158 x 198 x 380		213 x 145 x 436	
Net Weight (kg)	3.55	4.25	4.7	7.8	8	10.1	10.5	19.8	23
OPERATING ENVIRONMENT									
Humidity	0-90 % RH @ 0- 40°C (non-condensing)								
Noise Level	Less than 40dB								
MANAGEMENT									
Optional USB/RS-232 Port	Supports Windows® 2000/2003/XP/Vista/2008, Windows® 7, Linux, Unix, and MAC								



ATENCO

ATENCO POWER TECH CO. LTD

2F-7 No.14, Xiwei St., Sanzhong Dist., New Taipei City 24155, Taiwan

TEL +886-2-2280-6939 FAX +886-2-2280-2939 info@atenco.com.tw www.atenco.com.tw