



Product Specification

Model: LiFePO4 76.8V 105Ah

ELITE NO.: ELT768105G

Date: 2023.03.16

Prepared By	Checked By	Approved By
Bingshan Chen	/	Guich Deng

Stored Power Solutions LLC

Tel: (941) 243-1460

<https://storedpowersolutions.com>

Email: sales@storedpowersolutions.com

Address: 13747 65th Street North, Largo, FL 33771



1. Specifications

No.	Item	General Parameter	Remark
1	Nominal Voltage	76.8V	
2	Rated Capacity	105Ah	
3	Cycle Life	≥4000 Cycles	Charge: CC@20A to 87.6V, then CV till current to 0.05C; Rest: 30min; Discharge: 100A to 60.0V; Temperature: 20±5°C.
4	Discharge Cut-off Voltage	60.0V	
5	Charge Cut-off Voltage	87.6V	
6	Material	LiFePO4	
7	Recommend Charge Current	100A	
8	Max. Continuous Charge Current	100A	
9	Max. Continuous Discharge Current	200A	Peak: 400A, @<35s
10	Operation Temperature	Charge: 0~55°C	
		Discharge: -20~65°C	
		Storage: 0~45°C	
11	Self-discharge Rate	<3%/month	
12	Casing	Iron casing	
13	Weight	Approx.: 72Kg	
14	Dimension (L*W*H)	740*320*246mm(±2mm)	
15	Bluetooth Function	Yes	
16	Protection Grade	IP67	
17	Display Screen	Optional	
18	Charger	Optional	
19	Communcation	CAN/RS485	

2. Product Structure Design

Product appearance (for reference only)



3. Test Conditions, Methods and Electrical Performance

3-1 Test conditions

All tests shall be done under temperature: 15°C~35°C, relative humidity: (RH) 25%~85%, air pressure: 86kPa~106kPa except special appointment.

3-2 Measuring apparatus

- Voltage is measured by DC Voltmeter whose precision is higher than 0.5 grade and self resistance is higher than 1k Ω /V;
- Current is measured by Amperemeter whose precision is higher than 0.5 grade;
- Temperature is measured by Thermometer which has proper measuring range and its division value is lower than 0.5°C;
- The time used in measuring should be degressed in hour, minute or second, and should have degree of accuracy no less than $\pm 1\%$.

3-3 Standard charge

Charge the battery with DC stable power supply 87.6V, constant current 20A until current reach to 0.05C(A).

3-4 Standard discharge

Charge battery by (3-3), discharge the battery with constant current 100A until the battery reach to over discharge protection or total voltage reach to 60V.

3-5 Battery capacity

Discharge battery by (3-4), and write down discharge time (hour), then capacity (Ah)=100A * discharge time (hour).

3-6 Electrochemistry performance

Item	Test Method	Technical requirement
20°C discharge capacity	Battery charge with standard methods, discharge at 100A, write down discharge capacity.	≥95% nominal capacity
55°C discharge capacity	Battery charge with standard methods, stored for 5h in 55°C±2°C, then discharge at 100A to cut-off voltage, write down discharge capacity.	≥80% nominal capacity
Charge retain ability and recover capability	Battery charge with standard methods, stored for 28d in normal temperature 7d in 55°C.	capacity retention rate≥80% capacity recover rate≥90%
Cycle life	Under the condition of 20°C±5°C, charge the battery with 20A; discharge the battery at 100A to 40V. Repeat the above test cycle till the retained capacity is 80% of initial capacity.	≥4000 cycles



4. Product Storage & Transportation

Storage	Transportation	Maintenance
<p>If the battery pack needs to be stored for a long time, charge the battery to 50% SOC (after discharge, charge by charger for 2~3h every 3 months).</p> <p>Battery pack and the charger should be stored in a clean, dry and ventilating place, and should not be placed together with corrosive material, keep the battery away from fire and heat source.</p>	<p>Battery pack and charger should be transported after packaging, and should avoid severe vibrating, impacting, extrusion, direct light and rain. They can be transported by automobile, train, ship, plane, etc..</p>	<p>a) The battery pack should be stored in 40%~60% state-of-charge.</p> <p>b) In the process of maintenance, don't assemble and disassemble the battery without permission, otherwise, the performance of battery will be descend.</p>

5. Inventory List of Articles



A



B



C



D

No.	Items	Quantities	Specifications	Remark
A	Battery Pack	1	Golf cart battery	Yes
B	Charger	1	DD-E22 (1600W)	Optional
C	LCD Display	1	ELT-LCD02-RS485	
D	External Power Cable	1	Cable (4AWG, Standard Overcurrent 200A)	

6. Warnings

- * Do not immerse the battery into water or seawater.
- * Do not use, leave or charge the battery near a heat source such as fire or heater.
- * Do not inversely connect positive and negative polar.
- * Do not put the battery in fire or heat the battery.
- * Do not short-circuit the battery with wires or other metals.
- * Do not pierce the shell with nails or other sharp objects. Do not hammer or tread the pack.
- * Do not disassemble the battery pack without permission.
- * Do not put the battery pack in microwave oven or pressure vessels.
- * Do not use the battery in extremely thermal environment, such as direct light or cars in hot day. Otherwise, the battery will overheats and the performance and life of battery will be influenced.
- * If the battery leaks or smells, move it away from open fire.
- * The battery should be used after fully charged in the first use.
- * If the battery pack smells, fevers, out of shape, color changes or any other abnormal phenomena happen when the battery is being charged or used, please take it out of the charger or electrical equipment.
- * If the battery leaks and the electrolyte contacts eye, do not rub eye. Instead, rinse eye with clean water, and seek medical attention immediately.
- * Temperature will influence discharge capacity, if the temperature exceeds standard environment temperature($25\pm 5^{\circ}\text{C}$), discharge capacity will reduce.

