

# DCS Wheel Well Add-On Instructions

[www.DCSLighting.com](http://www.DCSLighting.com)



Follow us on Facebook and Instagram @dcslighting

Each light is meant to mount in the top of the wheel well facing downwards. Use the supplied self-drilling screws to secure them into the plastic or aluminum fender liners. If installing them into the rear of your jeep without fender liners, prevent rust by using a sealant to waterproof holes. Route wires away from exhaust or any moving parts. Use the supplied zip-ties and self-adhesive clips to secure wire after installation. If possible, route wire behind the fender liner to keep away from the wheels.

Front lights are designed to plug into the “C” harness along the firewall of your existing DCS rock light kit.

Rear lights are designed to plug into one of the plugs at the end of your “A” and “B” harnesses on each side. On JK and JT models, use the small oval hole just above the brake line bracket as pictured.

JK



JT

