

Intercom for Sound, Lighting and Production Professionals

BP1SL

(Switchable Between Circuit A <u>or</u> Circuit B) Portable Headset Station





- Performance
- Durability
- Value
- Compatibility

Performance: The BP1SL is designed to be connected to two different circuits, but may only communicate with one at a time. When the user is connected to either circuit, the signal lamp for the other is still active. The BP1SL portable headset station may be worn on the belt or hung on the wall by its sturdy belt-clip. Soft plastic strips on the underside help hold it in place when set on top of a console. The matte black finish minimizes visibility. Frequency response has been carefully shaped to optimize both intelligibility and long-term listening comfort. A mic limiter circuit reduces overload distortion. The high bridging impedance ensures that system and sidetone levels do not vary as other stations are switched in and out of the circuit.

The top (front) panel contains controls for switching the microphone on and off, for controlling listening level, for signaling, and for switching between circuits A and B. The are easily identifiable by touch. A recessed, screwdriver-adjust control is provided for varying the level of the user's voice to be heard in his own earphone (sidetone). A pair of long-life, extremely bright, red LEDs serve as the signal lights. The bottom panel provides one 3-pin female XLR for connection to each circuit, and a 4-pin male XLR for connection of any standard communications headset with a dynamic microphone.

Durability: The ribbed, extruded aluminum case; glass-filled nylon end bezels; internal support system for the PC board; best quality XLR connectors, and; recessed controls, all contribute to the outstanding ability of the BP1SL to withstand rough usage.

Value: The comparatively low price of the BP1SL is made possible by the minimized assembly cost resulting from simplicity of construction. Simple construction also affords the use of higher quality components, and increases the ease (thus lowering the cost) of servicing.

Compatibility: The BP1SL is plug-in compatible with Clear-Com® and other popular headset intercom systems.

Technical Specifications: (Subject to change without notice)

Power requirement: 24~30VDC, 10mA quiescent, Sidetone rejection: 50dB

30mA max. (with signal lamp lit)

Audio bridging impedance: 200 unbalanced

Headphone output: 8 ~ 4K acceptable, 200 ideal Size: 3.70 x 4.30 x 2.50 in. (93.98 x 109.22 x 63.5 mm)

Microphone input: 200~600 Dynamic; 1.2~1.8k electret Weight:13.5oz.(0.383Kg.)

Pro Intercom LLC

PO Box 7035 Algonquin Illinois 60102-7035

Phone: +1 (815) 680-5205 Orders and Tech support: (888) 320-5928 Fax: +1 (815) 526-8689

support@prointercomllc.com Skype: intercom4pros

Printed in U.S.A. Rev.3_01.13