



Figure 1 – Fuse Block

Fuse Position	Amps	Circuits Protected
1	15	Radio, Tape Deck, CB Radio, Power Antenna
2	20	Speed Control, Cornering Lights, Trunk Release Solenoid, Illuminated Entry, A/C, ATC Clutch, Power Window Relay (4 door models), Door Open Warning, Rear Window Deice Relay, Moonroof Relay, Police Circuits Relay
3	20 _{ckt bkr}	Power Windows (2 door models)
4	—	Blank
5	4	Instrument Panel Illumination, Radio Illumination
6	20 or 35	20 with Heater Blower; 35 with A/C or ATC Blower
7	20	Backup Lights, Turn Signal Lights
8	15	Stop Lights, Hazard Flasher
9	15	Courtesy Lights: Dome, Map, Glove Box, Console, Trunk, Vanity Mirror; Illuminated Entry, Clock (without Gages), Reminder Buzzer, Seat Back Latch Relay
10	30 or 20 _{ckt bkr}	Cigar Lighter, Clock (with Gages), Seat Back Latch Solenoids (2 door models), Power Seats, Power Door Locks
11	7½	Carburetor Circuits, Seatbelt Warning, Warning Lights