

Digital Counter Upgrade Rewire Instructions

1. Locate Calculator sensor wire on both the pickup and the caker. (Grey Wire)
2. Disconnect and remove all the Grey Calculator wire.
 - a. (Remove your 4 prong plugs if on a plug Kit)
 - b. You will not need the 4 prong plugs anymore.
3. Remove the magnet from the sprocket and remove the sensor magnet from the post on the gear box. (ALL OF THE MAGENT AND GLUE MUST BE REMOVED FROM THE SPROCKET.)



4. Run the new sensor wire where you removed the old calculator wire.
5. Wire up your 6 prong plugs according to the table below if you are on a plug kit.

BROWN	TM -OR- T
BLACK	GD -OR- G
BLUE	LT -OR- L
PUSH BUTTON	Black on AS -OR- S White on RT -OR- R

6. Mount the sensor with brackets around the post that you removed the magnet from.
7. Re-tuck all exposed wires, hook up pierce counter in cab of vehicle, and test.



Trouble Shooting:

If counter does not count, screw sensor closer to sprocket tab and test again. If the problem persists, please call the number located on your counter.