

Temperature Sensor (PT 7-MA)

General Description

The Wireless Temperature Sensor uses a type NTC thermostat to measure temperature.

Features

- Multifunction thermometer
- Detect the temperature and show it on the screen.
- The users can set the ceiling and floor temperature.
- If the real temperature is higher than ceiling temperature or lower than floor temperature, it will send the signal to Picars Management System.



Specifications

Model No.	PT 7-MA
Operating voltage	9V battery (250 mAH)
Static Current	≤ 60 uA
Alarm Current	≤ 30 mA
Radio Frequency	433 MHz
Transmitting Distance	≤ 80m (in open area)
Temperature Detection	-29 to +90 (C°)
Temperature Record	28 hrs
Operating Temperature	-10 C° ~ +50 C°
Installation	Surface Mounting
Humidity	≤ 85%