

Project Name:		_
Part Numbers:	Date:	_

Features

- Mechanical Latching Relays
- Status Indicator
- Manual Override Lever
- Option for Auxiliary Contact Relay

The Most Reliable Relays for Modern Lighting Solutions

The core of our panel systems is the HID (High In-Rush Duty) relay. These Universal Douglas relays have been the industry standard for decades because durable design provides reliable control for lighting and plugs loads and makes safety a priority. These mechanically latching relays require only a momentary pulse to change the state and requires **no energy** to maintain the state. They are available with an auxiliary contact output for low voltage status feedback to systems by others.

High "in-rush" currents can be 50 to 100 times the normal operating current and will damage any connected switching component not designed for that current. Our relays are rigorously tested, and UL certified to withstand excess in-rush currents.

Typical Applications: upto 20A lighting load ON/OFF switching

PART NUMBER	DESCRIPTION
WR-6161	1-pole HID relay 20A: 120/277/347VAC
WR-6161-382	1-pole HID relay (auxiliary contact) 20A: 120/277/347VAC, Auxiliary contact: 1A, 125VAC


WR-6161 HID Relay

Manual Switch Lever & Indicator Load Terminals Auxiliary Contacts (WR-6161-382 only)

Dimensions

Inches [mm]

Relays mount to a snap rail built into Douglas PWEx series relay panels



*Patent Pending Rev 8/1/2022 Douglas Lighting Controls





RELAY TECHNOLOGY

Panasonic relays utilize an ingenious control method that permits simple and minimal wiring. All functions for low voltage control: ON, OFF, indication and location are provided with only a 2-wire connection of which one is often a common.

OPERATION

- A negative pulse turns the relay ON and a positive pulse turns it OFF. Using a diode, an AC signal can be rectified to turn the relay either ON or OFF. Douglas switches have 2 diodes built into the switch to provide the ON and OFF signals.
- The relay has 2 similar diodes built inside that are in series with the relay coil. The diodes in the relay act as gates for the switch signal.
- To turn the relay ON or OFF, the rocker switch completes the circuit by selecting the ON or OFF diode. If the diode selected is in the same direction as the gate diode in the relay, the relay will switch. If the gate diode is not in the correct direction, then nothing will happen since the relay is already in the correct state for the action selected by the switch. When the switch is released, a spring returns it to the central neutral position.
- Indication (ON state) and location (OFF state) are obtained by
 utilizing LED diodes built into the switch. Only the LED which is
 connected in the same direction as the gate diode in the relay
 will light. Although the LED current passes through the relay
 coil, it is not large enough to cause the relay to trip. However,
 there is a limit: the maximum number of LED switches that can
 be connected to the same relay is 6.
- For additional convenience (especially during installation) all standard models have a manual control lever and indicator permitting a nonelectrical method of switching and status check at the panel.






*Patent Pending Rev 8/24/2022 Douglas Lighting Controls



CONNECTIONS



Technical Details

CONTROL INPUT	 Class 2 circuit 0.350A (350mA) 24V reversible polarity pulse Input terminals: #16 - #20AWG Output terminals: #10 - #14AWG 		
LISTINGS	UL		
OUTPUT	60,000 operations with 20A load, 2000A inrush @20 times / min. switch speed		
ENVIRONMENT	 Indoors, stationary, non-vibrating, non-corrosive atmosphere and non-condensing humidity Ambient temperature: 15°F to 120°F (-10°C to 50°C) 		
WARRANTY	Standard 5-years		

*Patent Pending Rev 8/24/2022 Douglas Lighting Controls