



#### CHARGE TIMES

- Wall Charger (72W): 5 Hours
- Car Charger (30W): 13 Hours
- Nomad 28 Plus Solar Panel: 23-58 Hours
- Boulder 50 Solar Panel: 13-32 Hours
- Boulder 100 Solar Panel: 6.5-16 Hours
- Nomad 100 Solar Panel: 6.5-16 Hours
- Boulder 200 Solar Panel: 4-8 Hours (NOTE: Connecting the Yeti 400 to the Boulder 200 Briefcase requires an [Anderson to 8mm Connector](#) cable)

#### GENERAL

- Product SKU: 23000
- Chainable: Yes
- Weight: 29 lbs (13.2 kg)
- Dimensions: 10.25 x 8 x 8 in (26 x 20.3 x 20.3 cm)
- Operating Usage Temp: 32-104 F (0-40 C)
- Certs: CE, FCC, ROHS
- Warranty: 6 months

#### PORTS

- USB port (output): 5V, up to 2.1A (10W max) regulated
- 6mm port (output, 6mm, green, hexagon): 12V, up to 10A (120W max)
- 12V car port (output): 12V, up to 10A (120W max)
- AC inverter (output, 60Hz, pure sine wave): 110V, 2.6A (300W continuous, 600W surge max)
- Power Pole Chaining Port: 12V, up to 33A (400W max)
- Charging Port (input, 8mm, blue, circle): 14-29V, up to 10A (120W max)

#### BATTERY DETAILS

- Cell Type: AGM Lead-Acid
- Peak Capacity: 396Wh (12V, 33Ah)
- Lifecycles: hundreds of cycles
- Shelf-Life: Keep plugged in, or charge every 3-6 months
- Fuses: none
- Management System: Charging and low-battery protection built-in