

## Aurora A6 Profile Spot Zoom 15-45 °

10ch mode- A Mode Displays A before address

01	Main Dimmer
02	Strobe
03	Reserved/Unused
04	Reserved/Unused
05	Red
06	Green
07	Blue
08	Lime
09	Amber
10	Cyan

6ch Mode- D Mode Displays D before address

01	Red
02	Green
03	Blue
04	Lime
05	Amber
06	Cyan