

# Configure an Audio Conference Bridge

## Scope:

The following document will show you how to configure a audio Conference Bridge.

## Requirements:

- Access to the Manager Portal
- An Owned or Dedicated Conference Bridge
- A DID for the Conference Bridge


## Types of Conference Bridges

The PBX Portal allows you two types of conference bridges:

- Dedicated Conference Bridge: Shared among all users. Use caution because it is possible for multiple hosts to attempt to use the same conference bridge.
  - Owned Conference Bridge: Private to an individual user.
-

# Provisioning a Dedicated Conference Bridge

1. Navigate to **Conferences**.



2. Click on **Add Conference**.



3. Enter a **name** for the conference bridge.
4. Select **Type: Dedicated conference bridge**.
5. Select an available **extension number** between 9200 and 9299.
6. Select a **Direct Phone Number** to use for the bridge.
7. Create a 4 to 6 digit **Leader PIN**.
8. Create a 4 to 6 digit **Participant PIN**.
9. Complete the remaining options per your preferences.
10. Click **Save**.


## Add a Conference



Name  

Type  Dedicated conference bridge  
 Owned conference bridge


Extension  **Note:** Extension cannot be changed

Direct Phone Number  

Leader PIN

Participant PIN

Max Participants  Unlimited 50 99

Minimum participants to start  


Options  Require a Leader to start  
 Prompt all participants for their name  
 Announce participant arrivals/departures

Cancel

Save

# Provisioning an Owned Conference Bridge

1. In the PBX Portal go to **Domain > Conferences**.



2. Click on **Add Conference**.



3. Enter a **name** for the conference bridge.

4. Select **Type: Owned conference bridge**.

5. Select the **Owner extension**.

6. Select an available extension number between 9200 and 9299 that can be used to dial directly into the conference.

7. Select a **Direct Phone Number** to use for the bridge.

8. Create a 4 to 6 digit **Leader PIN**.

9. Create a 4 to 6 digit **Participant PIN**.

10. Complete the remaining options per your preferences.

11. Click **Save**.

## Add a Conference



Name

Type  Dedicated conference bridge  
 Owned conference bridge

Owner  **Note:** Owner cannot be changed

Direct Dial

Direct Phone Number

Leader PIN

Participant PIN

Max Participants  Unlimited 50 99

Minimum participants to start

Options  Require a Leader to start  
 Prompt all participants for their name  
 Announce participant arrivals/departures

Cancel

Save