

Specs

5000 Watt Portable Generator with CO Guard®

Model Number

030737

Engine Brand

B&S OHV

Running Watts*

5000

Starting Watts*

6250

Volts

120 / 240

Engine Displacement (cc)

389

CO Guard

Yes

Fuel Tank Capacity (gal)

7.5

Run Time

12 hrs @ 50% load

Alternator

Power Surge™

Start Type

Recoil

Low Oil Shutdown

Yes

Muffler

Super Lo-Tone

Fuel Gauge

Yes

Hour Meter

Yes

Wheel Diameter (in)

10

Automatic Voltage Regulation

Yes

Spark Arrestor

Yes

Width (in)

27.2

Weight (lbs)

187

Height (in)

28

Length (in)

28.4

Consumer Warranty (Product) **

2-Year Limited

Commercial Warranty (Product) **

1-Year Limited

OHV Engine

Yes

*Generator per PGMA (Portable Generator Manufacturers' Association) standard ANSI/PGMA G300-2018, Safety and Performance of Portable Generators **Per Briggs & Stratton 628K *** See Operator's Manual for complete warranty details.