

☑ 5500 Watt Portable Generator with CO Guard<sup>®</sup> **Model Number** 030744 **Engine Brand** B&S OHV **Running Watts\*** 5500 Starting Watts\* 6875 Volts 120/240 **Engine Displacement (cc)** 389 Fuel Tank Capacity (gal) 7.5 **Run Time** Up to 12 hours at 50% load Alternator Power Surge<sup>™</sup> Start Type Recoil Low Oil Shutdown Yes Muffler Super Lo-Tone™ **Fuel Gauge** Yes **Hour Meter** Yes Wheel Type Never-Go-Flat **Automatic Voltage Regulation** Yes **Spark Arrestor** Yes Width (in) 27.2

Weight (lbs)
190
Height (in)
28
Length (in)
28.4
Consumer Warranty (Product) **
2-Year Limited
Commercial Warranty (Product) **
1-Year Limited
OHV Engine
Yes

\* Generator per PGMA (Portable Generator Manufacturers' Association) standard ANSI/PGMA G300-2018, Safety and Performance of Portable Generators.

\*\* See Operator's Manual for complete warranty details.

<sup>+</sup> Sound levels may vary based on proximity and location; measured 1/4 load at 7 meters from control panel side.