

Specs

6250 Watt Portable Generator

Model Number

030728

Engine Brand

Briggs & Stratton®

Running Watts*

6250

Starting Watts*

8500

Volts

120/240

Engine Displacement (cc)

420

Fuel Tank Capacity (gal)

7.5

Run Time

Up to 11 Hours @ 1/2 Load

Alternator

Power Surge™

Start Type

Recoil

Low Oil Shutdown

Yes

Muffler

Super Lo-Tone™

Fuel Gauge

Yes

Hour Meter

Yes

Wheel Type

Never Go Flat

Wheel Diameter (in)

10.0

Width (in)

27

Weight (lbs)

210

Height (in)

28

Length (in)

28

Consumer Warranty (Product) **

2-year Limited

Commercial Warranty (Product) **

90-day Limited

Running Amperage

26

Starting Amperage

52.1

Idle Control

No

Engine Series

1850 Series™

OHV Engine

Yes

Warranty Commercial Product

90-day Limited

*Generator per PGMA (Portable Generator Manufacturers' Association) standard ANSI/PGMA G300-2018, Safety and Performance of Portable Generators.

**See Operator's Manual for complete warranty details