

# Specs

**P2200 PowerSmart Series™**

---

<b>Model Number</b>	030651
<b>Starting Watts*</b>	2200
<b>Running Amps</b>	14.16
<b>Engine Displacement (cc)</b>	110
<b>Fuel Tank Capacity (gal)</b>	1
<b>Alternator</b>	Permanent Magnet
<b>Low Oil Shutdown</b>	Yes
<b>Muffler</b>	Super Lo-Tone™
<b>Hour Meter</b>	No
<b>Decibel† dB(A)</b>	59
<b>Weight (lbs)</b>	54
<b>Length (in)</b>	21
<b>Commercial Warranty (Product) **</b>	90-day
<b>Running Watts*</b>	1700
<b>Volts</b>	120
<b>Surge Amps</b>	18.33
<b>OHV Engine</b>	Yes
<b>Run Time</b>	up to 8.0 @ 25% Load
<b>Start Type</b>	Recoil
<b>Automatic Idle Control</b>	Yes
<b>Fuel Gauge</b>	No
<b>Spark Arrestor</b>	Yes
<b>Width (in)</b>	12.5
<b>Height (in)</b>	17.35
<b>Consumer Warranty (Product) **</b>	2-year Limited

\*Generator per PGMA (Portable Generator Manufacturers' Association) standard ANSI/PGMA G300-2015, Safety and Performance of Portable Generators.

\*\*See Operator's Manual for complete warranty details