

# Specs

**P2400 PowerSmart Series™ Inverter Generator with CO Guard®**

**Model Number**

030758

**Engine Brand**

B&S OHV

**Running Watts\***

1800

**Starting Watts\***

2400

**Volts**

120

**Engine Displacement (cc)**

79

**CO Guard**

Yes

**Bluetooth**

-

**Fuel Tank Capacity (gal)**

1

**Run Time**

Up to 8 hours at 25% load

**Start Type**

Recoil

**Low Oil Shutdown**

Yes

**Muffler**

Super Lo-Tone

**Fuel Gauge**

No

**Hour Meter**

No

**Automatic Voltage Regulation**

Yes

**Spark Arrestor**

Yes

**Decibel† dB(A)**

62

**Width (in)**

12.2

**Weight (lbs)**

50.4

**Height (in)**

17.4

**Length (in)**

20

**Consumer Warranty (Product) \*\***

36 Months

**Commercial Warranty (Product) \*\***

12 Months

*\*Generator per PGMA (Portable Generator Manufacturers' Association) standard ANSI/PGMA G300-2018, Safety and Performance of Portable Generators \*\*Per Briggs & Stratton 628K \*\*\* See Operator's Manual for complete warranty details.*