

Specs

P4500 E/S Manual Choke P4500 R/S

Model Number

030836

Engine Brand

B&S OHV

Running Watts*

3700

Starting Watts*

4500

Volts

120

Engine Displacement (cc)

224

CO Guard

Yes

Bluetooth

No

Fuel Tank Capacity (gal)

3.5

Run Time

16 hrs @ 25% load

Alternator

Permanent Magnet

Start Type

Electric

Low Oil Shutdown

Yes

Muffler

Super Lo-Tone

Fuel Gauge

Yes

Hour Meter

Yes

Automatic Voltage Regulation

Yes

Spark Arrestor

Yes

Width (in)

17.6

Weight (lbs)

104

Height (in)

20.3

Length (in)

24.5

Consumer Warranty (Product) **

3-Year Limited

Commercial Warranty (Product) **

1-Year Limited

Generator per PGMA (Portable Generator Manufacturers' Association) standard ANSI/PGMA G300-2018, Safety and Performance of Portable Generators **Per Briggs & Stratton 628K * See Operator's Manual for complete warranty details.*