

CA.81BB

8x Receiver Bodypack Wireless System in a 1 u case





FEATURES:

The Creative Audio Technology CA.81BB is an 8 receiver in a single 1u case true diversity wireless microphone system that runs off 2 pairs of antennas and comes with 8 CA.81B bodypack transmitters. The CA.81 is available in two frequency bands – G (490-530 MHx) and H (530-580MHz)

- Eight (8) true diversity receivers in a 1u rack case
- built-in antenna distribution 4 antennas total
- true diversity receivers ensure minimal drop outs
- up to 3 sets of 8 possible in most locations
- scan for open frequencies ~200 channels per band
- infra-red transmitter sync
- mute function and lock functions on all transmitters
- eight (8) true balanced XLR outputs + a ¼" mix output

WARRANTY – 24 MONTHS:

Reilly SR LLC – Creative Audio Technology – warrants this product against faulty materials or workmanship for 2 years from date of purchase. Coverage DOES NOT extend to physical damaged incurred after delivery, damage caused by failing to follow the guidelines in the instruction guide, damage caused by any attempt to repair the item by third parties or any product that has had its Serial Number erased, changed or removed. We will repair or replace items at our discretion.

FLAT RATE SERVICE:

We will repair your CA.81BB for a flat rate for any reason, failure out of warranty, broken, damaged. See www.bodymics.com.flatrateService.html for details.



SPECIFICATIONS:

Operating rie	quency	470-330. 330-300191112
Frequency Sta	bility	0.05%
Modulation Ty	/pe:	FM
Tuning Type: .		Phase Lock Loop
Frequency Res	sponse:	40Hz-18kHz
Signal to Nois	e Ratio:	>105dB
•		<+0/5%
Range:		. 160m (500ft) clear line of sight
Receiver:		
Balanced Line Out Level XLR Output:5v @ 2k		
Power Req	uirement:	12v DC @ 2A max
Dimension	s (WxHxD) 1	19" x 1.75" x 12" plus connectors
Weight (ne	:t)	4kg (8lb 13oz)
CA.81B Bodyn	ack Power Outp	out: 5mW or 10mW (select)
		<45dB
		: 2x AA Alkaline
	, ,	6- 8 hours
	,	

Dimensions: 4.25" x 2.375" x 0.8"

IN THE BOX:

- CA.81R 8x receiver
- 8x CA.81B bodypack transmitters
- 4x half-wave whip antennas
- 12x 2A power supply
- 16 A AA alkaline batteries
- Instructions