

**STEK CM108 Digital Clamp Meter T-RMS AC Current, Voltage, Resistance, Capacitance, VFD (Variable Frequency Drive Measurement), Temperature Measurement**



**Features:**

- Can measure AC/DC voltage, AC current, resistance , capacitance, duty, temperature, Frequency NCV and test continuity.
- Manual or Auto measurement function and range.
- Overload protection for the whole measurement range.
- LCD with double color light,when measuring big voltage and current, it automatically turns orange red color, more safe !
- Data hold function, low battery indication, auto power off.
- AC bandwidth, Diode test
- Suitable for electrical equipment testing and maintenance.

**STEK CM 108 Specifications:**

Function	Range	Accuracy
		DMM 108
DC Voltage	6V/60V/600V/1000V	±(1.0%+3)
AC Voltage	6V/60V/600V/750V	±(1.2%+3)
AC Current	60A/600A/1000A	±(3.0%+5)
Resistance	600Ω/6kΩ/60kΩ/600kΩ/6MΩ/60MΩ	±(1.0%+3)
Capacitance	10nF/100nF/1μF/10μF/100μF/1mF/10mF	±(4.0%+3)
	100mF	±(5.0%+5)
Frequency	10Hz/100Hz/1kHz/10kHz/100kHz/1MHz/10MHz	±(1.0%+3)
Duty	1%~99%	±(1.0%+2)
Frequency	10Hz/100Hz/1kHz/10kHz/100kHz/1MHz/10MHz	±(1.0%+3)
Duty	1%~99%	±(1.0%+2)
Temperature (°C/°F)	-40°C~1000°C	±(1.0%+3)
	-40°F~1832°F	±(1.0%+3)
Counts	6000	
Auto/Manual range	√	
Bargraph		
NCV	√((LED and Buzz))	
Diode	√	
Continuity	√((LED and Buzz))	
MAX/MIN hold	√	
Data hold	√	
True RMS	√	
AC bandwidth	1kHz	
Low battery indication	√	
Auto power off	√	
Double color backlight	√	
Flashlight	√	
LPF		
Power	2XAA Batteries	
Safety Rating	EN61010-1,-2-030 EN61010-2-033, EN61326-1 CAT III 1000V,CATIV 600V	

**Accessories:**

- CMM 108 Clamp Meter
- Test Leads CAT III 1000V, CATIV 600V
- K-Type Temperature Probe
- Carrying Case

