

Air-Cooled Standby Generator

GENERAC®

The Generac Standby Generator is the most advanced air-cooled standby generator providing unparalleled peace of mind. It provides the automatic backup power you need to help protect your home and family during a power outage. Connected to your existing LP or natural gas fuel supply, it kicks in within seconds of sensing power loss—automatically—and runs for as long as necessary until utility power returns.



Cellular Connectivity

Built-in Cellular Connectivity allows you to monitor performance and control your generator with Mobile Link whether you're home or away.



Cost of Ownership

Lowest total cost of ownership.*

**Based on MSRP + average maintenance cost of equivalent solutions.*



Seamless Energy Integration

Compatible with ecobee by Generac thermostats and Generac PWRcell battery systems to seamlessly monitor and control your home's energy.



Unmatched Power

28kW is the most powerful air-cooled standby generator in the market, setting a new standard for whole-home backup power.



Improved Performance

Electronic Fuel and Emission Control to adjust to the environment which improves cold starting and performance when operated in cold climates.

Get an estimate today!



24/7/365 Customer Support Team

Standing by all day, every day from our headquarters in Wisconsin to answer any questions you might have.



Built in the USA*

Generac generators, engines and automatic transfer switches are engineered and built in the USA.*

**Assembled in the USA using domestic and foreign parts*



5-Year Limited Warranty

Included with all air-cooled standby generators.

Air-Cooled Standby Generators



SPECIFICATIONS (LP/NG)	10kW	14kW	18kW	20kW 3Ph	22kW	24kW	26kW	28kW
Generator Only Model	7257	7258	7259	7271	7260	7261	7327	7282
Generator / 200 Amp Auto Transfer Switch	7321 16ct	7323	7324	N/A	7325	7326	7328	7329
Rated kW LPG/NG*	10/9*	14/14*	18/17*	20/20*	22/21*	24/22.5*	26/24*	28/25*
Voltage (Single Phase)	240							
Amps @ 240V LPG*	42	58	75	69	92	100	108	116
Amps @ 240V NG*	38	58	71	69	88	94	100	104
Operating RPM	3600							
Engine	Generac G-Force 400 Series	Generac G-Force 800 Series		Generac G-Force 1000 Series				
Engine Displacement	459cc	817cc		997cc				
Electronic Fuel and Ignition Control (EFIC)	Yes							
Hydraulic Lifters	Yes							
Fuel Consumption @ ½ Load – NG cu. ft/hr	98	189	164	189	221	197	182	182
Fuel Consumption @ Full Load – NG cu. ft/hr	132	243	235	290	311	291	316	297
Fuel Consumption @ ½ Load – LPG cu. ft/hr (gal/hr)	35 (0.94)	63 (1.76)	60 (1.65)	72 (1.99)	89 (2.45)	89 (2.45)	74 (2.05)	81 (2.23)
Fuel Consumption @ Full Load – LPG cu. ft/hr (gal/hr)	58 (1.60)	106 (2.92)	105 (2.87)	123 (12.86)	135 (3.71)	135 (3.71)	144 (3.95)	144 (3.97)
Quiet-Test Mode	Yes							
Smart Exercise	Yes							
Exercise with Transfer of Power	Yes							
db(A) at Low Speed Exercise (Quiet-Test Mode)	49	55						
db(A) at Normal Operating Load	61	65		67				
Enclosure	Aluminum							
Enclosure Color	Metro Gray							
Warranty	5 – Year Limited							
Dimensions (L x W x H) in/cm	46.4 x 26.3 x 30.7 / 117.9 x 66.8 x 77.9							
Weight (lb)	334	391	426	472	451	461	524	524
Mobile Link Cellular Connectivity as Standard	Yes							
Bundle Includes ecobee by Generac	No	No	No	No	No	No	No	Yes

*Maximum kilovolt amps and current are subject to and limited by such factors as fuel BTU/megajoule content, ambient temperature, humidity, barometric pressure, altitude, engine power and condition, etc. Maximum power decreases approximately 3.5% for each 1,000 ft (304.8 m) above sea level; and also will decrease approximately 1% for each 10 °F (6 °C) above 60 °F (16 °C).

GENERAC®

NATIONWIDE INSTALLER SERVICE NETWORK

Generac's commitment to service includes scheduled maintenance programs, warranty assistance and emergency service to help ensure that Generac customers are never left powerless. The largest nationwide network has factory-trained technicians on staff and maintains large inventories of Generac parts, components and accessories. Find an installer near you at Generac.com.

Generac Power Systems, Inc.
S45 W29290 Hwy. 59, Waukesha, WI 53189

www.Generac.com | 888-GENERAC (436-3722)

201911325 REV 07/26

©2026 Generac Power Systems. All rights reserved.
Specifications are subject to change without notice.