



## 'CALMATE' FIELD CALIBRATION KIT



- Σ Windows® PC compatible
- Σ Simple step by step operation
- Σ No Power Supply required
- Σ Integral HI Resolution Milliamp meter
- $\Sigma$  No test equipment required

Sigma Controls 'CALMATE' is a system to permit user calibration of all Sigma Controls level and pressure transmitters in the field.

Consisting of a protocol converter ("dongle") with USB cable, transducer connections and a program and instruction diskette, this kit allows for complete check and recalibration of any installed Sigma level transducer, manufactured since January 2011.

The unit powers the transmitter from the USB port on the P.C. and the protocol converter contains a highly accurate milliamp meter, which is displayed on the calibration screen.

Multiple parameter adjustments can be made to the transducer under calibration including Zero, Span, Range, Modbus I.D., Sample rate, offset, etc...

VISIT OUR WEBSITE SIGMACONTROLS.COM

## 'CALMATE' FIELD CALIBRATION KIT

Step 1: Find CallMate	COM5	Find Cal'M	ate	Note:	EXIT	
Step 2: Find Unit on ModBus	Found Unit on ModBus	Find Uni	t		To read current from non-Sigma sensors:	
Step 3: Read Unit Data	Data read from unit	[Re]Read	Jnit	Use steps 1 and 4 only!		
CURRENT SETTINGS						
Firmware Rievision:	4.1					
Unit Serial Number	-00					
Sensor Temperature	23.2	Stop 4:	Rea	Read Loop Current 18.17 mA		
Engineering Units	PSI		noa		[Normal Riange 4.0mA - 20mA ]	
					[Max Range 3.5mA · 20.5mA ]	
Setting	Current Setting	Change Setting	ito Cl	ick to Change		
4mA Point	.00			Change 4mA Point	Sets 4mA point [Number can have 2 decimals	
20mA Point	100.00			Change 20mA Point	Sets 20mA point [Number can have 2 decima	
Current Reading	88.38			Correct Reading	Change this ONLY if you know the current reading has diffed.	
Offset Correction	.00	[ Desired Reading Remove Correc	[ Desired Reading ] Remove Correction <<< Use this to restore the uncorrected reading			
Caution: For /	Advanced Users O	nly				
Setting	Current Setting	Change Setting	to Cl	ick to Change		
ample Rate	Max Rate			Change Sample Rate	U=maximum, else ~ 1 to 127 sec delay	
#Readings to Average [1 - 32]	1			Change # Readings	Range is 1 - 32 readings to do a rolling average on	
ModBus Node #	17			Change Node #	Valid Modbus node numbers are from 1 · 246	
Raw Sensor Counts	37937	-			Use "Find Unit" to verify changed ModBus node #	
	Lerow	For diagnostic use Sigma Controls in				

SOFTWARE VERSION V4.1

