

INSULATION RESISTANCE METER MIC-2501

**INSULATION
RESISTANCE
MEASUREMENT
UP TO
1TΩ
IN ACCORDANCE
WITH IEC 61557-2**



- **Insulation resistance measurement:**
 - selectable measurement voltage in the 100...2500 V range with 100 V step,
 - continuous indication of insulation resistance or leakage current,
 - automatic discharge of capacitance of tested object after the insulation resistance measurement,
 - acoustic signalling of five-second periods to facilitate obtaining time characteristics,
 - measured test times T1, T2 i T3 to measure one or two absorption coefficients in 15, 60 and 600 s,
 - indication of actual test voltage during the measurement,
 - protection against measuring live objects,
 - two and three-lead measurement method,
- **Continuity measurement of protective and equipotential conductors according to EN 61557-4 with the >200 mA current.**
- **Leakage current measurement.**
- **Measurement of alternating and direct voltages in the 0...750 V range.**
- **Built-in rechargeable battery pack.**
- **The instruments meet the requirements of the EN 61557 standard.**
- **The ability to charge from car lighter (12 V) socket (additional accessories).**

Sonel S.A.
Wokulskiego 11
58-100 Świdnica
tel. +48 74 85 83 860
fax +48 74 85 83 809

export@sonel.pl
www.sonel.pl

MIC-2501

Insulation resistance measurement (two-lead)

Measurement range acc. to IEC 61557-2 for $R_{ISOmin}=U_{ISOnom}/I_{ISOmax} \dots 1T\Omega (I_{ISOmax}=1 \text{ mA})$

| Range | Resolution | Accuracy |
|------------------|------------|------------------------|
| 0.0...999.9 kΩ | 0.1 kΩ | ±(3% w.m. + 20 digits) |
| 1.000...9.999 MΩ | 0.001 MΩ | |
| 10.00...99.99 MΩ | 0.01 MΩ | |
| 100.0...999.9 MΩ | 0.1 MΩ | |
| 1.000...9.999 GΩ | 0.001 GΩ | |
| 10.00...99.99 GΩ | 0.01 GΩ | |
| 100.0...999.9 GΩ | 0.1 GΩ | |

Values of measured resistance depending on measurement voltage

| Voltage U_{ISO} | Measurement range |
|-------------------|-------------------|
| up to 100 V | 50 GΩ |
| 200 V...400 V | 100 GΩ |
| 500 V...900 V | 250 GΩ |
| 1000 V...2400 V | 500 GΩ |
| 2500 V | 1000 GΩ |



Continuity measurement of protective connections and equipotential bonding with 200 mA current

Measurement range acc. to EN 61557-4: 0.10...999 Ω

| Range | Resolution | Accuracy |
|----------------|------------|-----------------------|
| 0.00...19.99 Ω | 0.01 Ω | ±(2% w.m. + 3 digits) |
| 20.0...199.9 Ω | 0.1 Ω | |
| 200...999 Ω | 1 Ω | ±(4% w.m. + 3 digits) |

- Voltage on open terminals: 4...24 V
- Output current at $R < 2 \Omega$: $I_{sc} > 200 \text{ mA}$
- Compensation of test lead resistance
- Current flowing in both directions, mean value of resistance is displayed

DC and AC voltage measurement

| Range | Resolution | Accuracy |
|-------------|------------|-----------------------|
| 0...299.9 V | 0.1 V | ±(3% w.m. + 2 digits) |
| 300...750 V | 1 V | ±(3% w.m. + 2 digits) |

- Frequency range : 45...65 Hz



Standard accessories:

- test lead banana plug; 1,8 m; 5 kV; red
- test lead banana plug; 1,8 m; 5 kV; blue
- test lead banana plug; 1,8 m; 5 kV; black
- USB cable
- "crocodile" clip 5,5 kV; black
- "crocodile" clip 5,5 kV; red
- "crocodile" clip 5,5 kV; blue
- pin probe 5 kV with banana connector; red
- pin probe 5 kV with banana connector; black
- carrying case
- power supply adaptor Z7
- meter harness
- DVD with software, including "SONEL Reader" (reading data from memory)
- calibration certificate
- warranty card

WAPRZ1X8REBB
WAPRZ1X8BUBB
WAPRZ1X8LB8B
WAPRZUSB
WAKROBL20K07
WAKRORE20K07
WAKROBU20K07
WASONRE0GB2
WASONBLOGB2
WAFUTM8
WAZASZ7

Electrical safety:

- type of insulation double, in acc. with EN 61010-1 and IEC 61557
- measurement category IV 600 V (III 1000 V) in acc. to EN 61010-1
- case protection rating in acc. with EN 60529 IP65

Other technical specifications:

- power supply of the meter NiMH 9.6 V - 2 Ah battery pack and power supply 12 V
- weight of the meter approx. 0,9 kg
- dimensions 200 x 180 x 77 mm
- display LCD segment display
- measurement results memory 990 cells, 11880 records
- transmission of measurement results USB

The acronym "m.v." stands for a "measured reference value".