



P1PE P2500i 2200W INVERTER GENERATOR

- 2200W Maximum output
- Compact, lightweight and portable
- ECO Mode, lowers engine RPM to increase fuel economy and lifespan
- Built In Recoil Start
- Automatic low oil level shutdown to protect the engine
- 230V 3 Pin UK Plug, 12v DC & 5v USB Sockets
- Ideal for camping, operating tools or backup power
- 4.2 hour runtime @ 50% load

SPECIFICATION

Model	P2500i
Engine Type	Hyundai 4 Stroke
Displacement	98cc
Rated Speed	5500rpm
Starting Method	Recoil
Fuel Type	Unleaded Petrol
Fuel Tank Capacity	4.5l
Fuel Consumption	
Oil Type	Semi-Synthetic 15W40
Oil Tank Capacity	350ml
Continuous Run Time	4.2h @ 50% load
Noise Level	58dB(A) @ 7m
Net Weight	22Kg

Sockets	1 x 230v 3 Pin UK Plug 1 x 12v DC 1 x 5v USB
Rated Output Power	2000w
Max Output Power	2200w
DC Output	12V / 5A
Frequency	50Hz
Accessories	Spark Plug Wrench Funnel

Rated Frequency	50Hz		
Rated Voltage	220V	230V	240V
Rated Current	4.0A	3.9A	3.75A