



Please note: Product might be different from pictures shown.
Specifications might vary due to continuous product development.

HY1000Si Petrol Inverter Generator

- 1.6hp 4 stroke petrol engine with low oil protection.
- Produces a maximum output of 1kW (1000w).
- Compact and lightweight design weighing 14kg.
- Low sound levels, just 58dB @ 7m.
- 2.2L fuel tank which provides a maximum runtime of 6.6hrs.
- ECO mode for low fuel consumption.
- Full LED display for quick and easy performance monitoring.
- Pure sine wave output for powering sensitive electronic appliances.
- 1 x 230v / 12v DC socket.

Specifications

MODEL	HY1000si
ENGINE MODEL	HX53 (XG - 144F)
ENGINE TYPE	OHV - Single Cylinder - 4 Stroke
ENGINE SIZE	53cc
OIL CAPACITY	250ml
FUEL	Unleaded Petrol
NOISE LEVEL	90/58dB (A) @ 7m
RATED SPEED	5500rpm
RATED POWER	0.9kW
MAX POWER	1kW
START METHOD	Recoil
FUEL TANK CAPACITY	2.2L
APPROX RUN TIME PER TANK	3.3hr @ 50% load
VOLTAGE	230VAC
FREQUENCY	50Hz
SOCKET TYPE	1 x 230 VAC / 3.9A
SOCKET TYPE	12 VDC / 5A
ALTERNATOR VOLTAGE REGULATION	Solid State Regulator
CASING	Plastic
BOX DIMENSIONS L x W x H	490mm x 280mm x 405mm
GROSS WEIGHT	17kg
FULLY ASSEMBLED DIMENSIONS L x W x H	451mm x 242mm x 379mm
DRY WEIGHT	14kg



T: 01646 687 880

E: info@hyundaipowerequipment.co.uk