

GEN 3 INSTRUCTIONS - DO NOT DISCARD

Here are some tips to help you enjoy your new all-in-one Starlink conversion

NETWORK

- The DEFAULT Network Name will be STARLINK or STINKY in all capital letters with no password.
- To change the wifi name and add a password for initial setup after applying power to your conversion, proceed to step 6 below. If you have forgotten your wifi password and need to reset the router, please follow all the steps below.
 1. If equipped, remove the metal mounting bracket from the rear of the dish to uncover the black rubber plug.
 2. Remove the black rubber plug.
 3. Apply power to the Starlink conversion.
 4. Utilize a small non-metallic object to depress the blue reset button behind the rubber plug.
 5. Reinstall the black rubber plug.
 6. Connect to the wifi named STARLINK or STINKY.
 7. Open the Starlink app and select "Router Not Configured" or go to "SETTINGS" then "ROUTER" to rename the wifi name and password.
- ***You must be logged in to the dishes associated account on the Starlink app to change the wifi name and password.***

ELECTRICAL

- *****PAY CLOSE ATTENTION TO THE + AND - POLARITY. WIRING IN REVERSE WILL RUIN THE UNIT WHICH IS NOT COVERED UNDER WARRANTY.*****
- Hardwire the provided receptacle and wiring harness DIRECTLY to the battery if at all possible **WITH THE PROVIDED 10GA WIRING HARNESS AND FUSE.**
- For more flexible/temporary use, you can find the provided 12v cigarette lighter adapter tip that will also thread onto your Starlink's male plug, there is a replaceable fuse in this tip also.

SNOW MELT MODE

- **Turn Snow Melt OFF using the Starlink App.** You must be logged into your associated Starlink account within the app. Just brush it off, it will work MUCH FASTER and does not drain your battery.

MOUNTING

- Mount on a roof location that DOES NOT POOL WATER, many RV roofs hold a lot of water near awnings, etc. the unit is sealed up, but not submersible.
- **WE DO NOT RECOMMEND UTILIZING SUCTION CUPS FOR MOUNTING**

Please feel free to reach out with any questions/concerns to: info@uniquecomponentry.com